

Ball Screw Actuator - Slider Type

ETH2 / ECH2 Series

Height reduction.




[ETH2/ECH2 Features]

Ball Screw Actuators

2nd Gen, compact design and **lower price!**

Grease Port Equipped

Improvement from 1st Gen.
Greasing from both side.



Different Motor Orientation



BC Inline



BL Left




BR Right



BM Bottom

Diverse Custom Options



Dual Carriages (Move separately)

Dual Carriages (Move together)

Extended Carriage

Opposite movement

Caged Ball Bearing

With no ball collision or friction, it significantly reduces movement noise, extends service life, and decreases maintenance frequency.



Top-down, Bottom-up mount

Direct mount without removing the cover.



Bottom

Top

C5 Ball Screw (Optional)

Standard C7 Ball Screw

Repeatability $\pm 5\mu\text{m}$


Optional C5 Ball Screw

Repeatability $\pm 3\mu\text{m}$

Higher Ball Screw RPM


- Up to **3600~4000rpm**
(Depends on the model)

Lower Center of Gravity



Low profile
Reduced weight and height. Makes overall design more compact whether use alone or in gantry configuration.


High Strength Structure



Mounting holes place right on top of the rail. Reduced vibration and increase stability while high speed application.

Reduced Height, Width and Weight

Unit:mm



ECH2 Clean Room Series Feature (Semi-Conductor Production Ready)

Air Fitting


Meet ISO4(Class 10)
with air fitting



Suitable for different environment

Offering Original and black color option.

Open and enclosed cover options. Optional cold plated ball screw and linear guide. Produce less dust, reduced wear, lower noise level, anti acid and no reflection. Only 2% reflection rate.



ISO CLASS Clean Room Certification

All certification are coming from authorized institution examine base on ISO 14644-1.



Clean Room Assembly

TOYO is few linear motion manufacturer in the world (Taiwan only) that can assemble actuators in clean room. Making sure minimized the contamination.



Application

Standard
Ball Screw Type
ETH Series

Standard
Belt Type
ETB / M

Cleanroom
Ball Screw Type
GCH

Cleanroom
Belt Type
ECB

Reference

Memo

Spec Index of Electric Actuator

ETH2 Ball Screw Actuator - Slider Type

Env.	Drive Type	Spec.	Motor Output (w)	Width (mm)	Repeatability (mm)	Ball Screw Spec		Reduce Ratio	Maximum Payload(kg)		Maximum Speed (mm/s)
						Outer Diameter (mm)	Lead(mm)		Horizontal	Vertical	
Standard	Ball screw	ETH2-14	400W	130	±0.005	14	6	-	110	40	360
							12	-	88	26	720
							24	-	40	20	1440
		ETH2-17	400W	152	±0.005	20	5	-	120	50	300
							10	-	110	30	600
							20	-	75	17	1200
		ETH2-22	750W	212	±0.005	25	40	-	15	15	2400
							5	-	150	60	300
							10	-	150	35	600
		ETH2-30	1500W	300	±0.005	32	25	-	100	18	1500
							10	-	250	48	400
							20	-	200	25	800
			750W	300	±0.005	32	32	-	105	12	1280
							10	3:1	400	130	200
							20		300	65	400
							32		180	38	640
							10	5:1	400	200	120
							20		300	110	240
							32		180	60	384

* Some specifications require an external regenerative resistor to reach the maximum load. For details, please refer to the data sheet of each product.

Dual Carriage Reverse Direction

Env.	Drive Type	Spec.	Motor Output (w)	Width (mm)	Repeatability (mm)	Ball Screw Spec		Reduce Ratio	Maximum Payload(kg)		Maximum Speed (mm/s)
						Outer Diameter (mm)	Lead(mm)		Horizontal	Vertical	
Standard	Ball screw	ETH2-14D	400W	130	±0.005	14	6	-	110	40	360
							12	-	88	26	720
							24	-	40	20	1440
		ETH2-17D	400W	152	±0.005	20	5	-	120	50	300
							10	-	110	30	600
							20	-	75	17	1200
		ETH2-22D	750W	212	±0.005	25	40	-	15	15	2400
							5	-	150	60	300
							10	-	150	35	600
		ETH2-30D	1500W	300	±0.005	32	25	-	100	18	1500
							10	-	250	48	400
							20	-	200	25	800
			750W	300	±0.005	32	32	-	105	12	1280
							10	3:1	400	130	200
							20		300	65	400
							32		180	38	640
							10	5:1	400	200	120
							20		300	110	240
							32		180	60	384

*Some specifications require an external regenerative resistor to reach the maximum load. For details, please refer to the data sheet of each product.

免費服務專線：台灣 0800-800-893
Toll-free Number Taiwan

Features

Standard
Ball Screw Type
ETH2

Standard
Belt Type
ETB / M

Cleanroom
Ball Screw Type
ECH2

Cleanroom
Belt Type
ECB

Multi Axis Type
XYGT / XYTH / XYTB

Reference

Stroke(mm) & Maximum Speed(mm/s)																												Speed		Page						
Stroke	50	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750	1800	1850		1900	1950	2000	2050	2100	
360				340	300	260	230	210	180	160	150	130	120	110	100	90																				-
720				680	600	520	460	420	360	320	300	260	240	220	200	180																				-
1440				1360	1200	1040	920	840	720	640	600	520	480	440	400	360																				-
300							275	250	225	200	183	167	150	142	133	117	108	100	92	83	75															-
600							550	500	450	400	367	333	300	283	267	233	217	200	183	167	150															-
1200							1100	1000	900	800	733	667	600	567	533	467	433	400	367	333	300															-
2400							2200	2000	1800	1600	1467	1333	1200	1133	1067	933	867	800	733	667	600															-
300							275	250	233	208	192	175	167	150	142	133	125	117	108	100	92	83	75	67											-	
600							550	500	467	417	383	350	333	300	283	267	250	233	217	200	183	167	150	133										-		
1500							1375	1250	1167	1042	958	875	833	750	708	667	625	583	542	500	458	417	375	333										-		
							400												383	367	333	317	300	283	267	250	233	217	200	183	167			-		
							800												767	733	667	633	600	567	533	500	467	433	400	367	333			-		
							1280												1227	1173	1067	1013	960	907	853	800	747	693	640	587			-			
														200																	183	167		-		
														400																	367	333		-		
														640																	587	533		-		
															120																			-		
															240																			-		
															384																			-		

Stroke(mm) & Maximum Speed(mm/s)																				Speed																		Page
Stroke	50	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750				
360							340	300	260	230	210	180	160	150	130	120	110	100	90																	-		
720							680	600	520	460	420	360	320	300	260	240	220	200	180																	-		
1440							1360	1200	1040	920	840	720	640	600	520	480	440	400	360																	-		
300										275	250	225	200	183	167	150	142	133	117	108	100	92	83	75												-		
600										550	500	450	400	367	333	300	283	267	233	217	200	183	167	150											-			
1200										1100	1000	900	800	733	667	600	567	533	467	433	400	367	333	300												-		
2400										2200	2000	1800	1600	1467	1333	1200	1133	1067	933	867	800	733	667	600												-		
300										275	250	233	208	192	175	167	150	142	133	125	117	108	100	92	83	75	67									-		
600										550	500	467	417	383	350	333	300	283	267	250	233	217	200	183	167	150	133									-		
1500										1375	1250	1167	1042	958	875	833	750	708	667	625	583	542	500	458	417	375	333									-		
							400												383	367	333	317	300	283	267	250	233	217	200	183	167				-			
							800												767	733	667	633	600	567	533	500	467	433	400	367	333				-			
							1280												1227	1173	1067	1013	960	907	853	800	747	693	640	587	533				-			
													200																			183	167		-			
													400																			367	333		-			
													640																			587	533		-			
														120																					-			
														240																					-			
														384																					-			

ETH2-14 1-axis

► Ball Screw Drive

精度
±0.005 mm



Max. stroke 1200mm

Max. Speed 1440mm/s

Motor Output 400W

Ball Screw ø14mm

Linear Guide 15X12.5-2pcs

Ordering Method

ETH2-14 - L6 - 500 - BC - T40B - C3N5L - Refer to the right page. - 0001

Model

Options

Customization Order No.

Stroke

50-1200mm
50 mm Pitch

Sensor location

L Left side
R Right side

Ball Screw Lead

6	6mm
12	12mm
24	24mm

Motor Position

BC	Motor Exposed
BL	Motor Left Side
BR	Motor Right Side
BM	Motor Bottom Side

Motor Brand & Power Output

M	Mitsubishi	10	-	B
P	Panasonic	20	-	
Y	Yaskawa	40	400W	
T	Delta	75	-	

*If No Brake, No Description.

Home Sensor

Out Side	
C	Motor Side
D	Opposite Motor Side
No Sensor	
E	No Sensor


Limit Sensor

Out Side	
3	1 Pc
4	2 Pcs
6	3 Pcs
7	4 Pcs
8	5 Pcs
9	6 Pcs
No Sensor	
5	No Sensor

*When the stroke is 50mm, Home + limit sensors is 2 maximum (only C3/D3/E3/E4/E5 can be selected)

Output type & Cable length

N5	NPN+5M Cable
P2	PNP+2M Cable
P5	PNP+5M Cable
-	NPN+2M Cable




Specification

Performance	Repeatability		mm	±0.005					
	Lead		mm	6		12		24	
	Maximum Rotating speed		rpm	3600	3000	3600	3000	3600	3000
	Maximum linear speed ※1		mm/s	360	300	720	600	1440	1200
	Maximum Payload	Horizontal	kg	110	110	88	88	40	50
		Vertical (No regenerative resistor)	kg	29	33	15	16	9	10
		Vertical (External 200W regenerative resistor)	kg	40	40	26	26	20	20
	Rated Thrust		N	1130		565		283	
	Stroke (increments)		mm	50-1200mm/ (50 increments)					
	Maximum acceleration		G	0.18	0.15	0.37	0.31	0.73	0.61
	Ball screw	Basic dynamic load rating Ca	N	7740		5866		3012	
		Basic static load rating Coa	N	14215		10408		5415	
	Linear Guide	Dynamic horizontal (100km)	N	29573					
		Static Horizontal	N	63504					
	Fixed bearing	Basic dynamic load rating Cr	N	8447					
Static load rating Cor		N	5060						
Parts	AC Servo Motor Output		W	400					
	Ball Screw Ø		mm	C7Ø14					
	High Rigidity Linear Guide		mm	W15XH12.5					
	Coupling		mm	14X10					
	Home Sensor	Outside		T64N(NPN)					


※1 During in a long stroke, it causes ballscrew deflection, the speed must reduce. (Please refer to the linear velocity from the data sheet below the dimension graph.)

Allowable Overhang




(Unit: mm)

Horizontal Installation		A	B	C
Lead 6	60kg	1600	137	140
	70kg	1340	112	115
	110kg	769	58	60
Lead 12	30kg	1142	264	247
	60kg	519	114	107
	88kg	319	66	62
Lead 24	20kg	454	271	188
	40kg	202	117	82
	50kg	151	86	60



(Unit: mm)


Wall Installation		A	B	C
Lead 6	60kg	140	137	1600
	70kg	115	112	1340
	110kg	60	58	769
Lead 12	30kg	247	264	1142
	60kg	107	114	519
	88kg	62	66	319
Lead 24	20kg	188	271	454
	40kg	82	117	202
	50kg	60	86	151



(Unit: mm)

Vertical Installation		A	C
Lead 6	25kg	388	388
	30kg	324	324
	40kg	243	243
Lead 12	10kg	781	781
	15kg	520	520
	26kg	300	300
Lead 24	9kg	485	485
	10kg	437	437
	20kg	218	218

Static Loading Moment



(Unit: N.m)

MY	479
MP	479
MR	423

* The data represented by the moment table is the center of gravity of the load. The length of the overhang is allowed in a single direction.

*Operation life is 10,000km when the product is using under the specified conditions.

*Data information is not for ceiling-mount inverse use. Contact us for the details if you want to apply ceiling-mount inverse usage.

*The life and torque are calculated by setting the motor acceleration and deceleration for 0.2 seconds.

Options

P - MM - CMK

Standard PIN hole		
Code	Instructions	Refer to
P	Standard PIN hole	P.677

Selectable Cable Leading Direction		
Code	Instructions	Refer to
MW	Upper side	P.679 ~ P.680
MM	Bottom side	
ML	Left side	
MR	Right side	

Additional keyway for motor drive parts				
Code	Instructions			Refer to
	Keyway Groove	Motor Position	Shipment Type	
CMK	Single (Limited to the motor side)	BC/M	Keyway Coupling	P.681 ~ P.682
		BL/BR/BM	Keyway Belt Pulley	
SKY	Double	BC/M	Keyway Coupling	
		BL/BR/BM	Keyway Belt Pulley	
SKN	Double	BC/M	Without Coupling (Please purchase and install by yourself)	
		BL/BR/BM	Without Belt Pulley (Please purchase and install by yourself)	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-14 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com •


BC Motor Exposed (Sensor on the left side)

Unit : mm




BC Motor Exposed (Sensor on the right side)

Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210
L	276	326	376	426	476	526	576	626	676	726	776	826	876	926	976	1026	1076	1126	1176	1226	1276	1326	1376	1426
A	90	20	70	120	50	100	30	80	130	60	110	40	90	20	70	120	50	100	30	80	130	60	110	40
M	1	2	2	2	3	3	4	4	4	5	5	6	6	7	7	7	8	8	9	9	9	10	10	11
N	4	6	6	6	8	8	10	10	10	12	12	14	14	16	16	16	18	18	20	20	20	22	22	24
KG	4.07	4.54	5.01	5.48	5.96	6.43	6.91	7.38	7.85	8.32	8.79	9.27	9.74	10.21	10.68	11.15	11.63	12.1	12.58	13.05	13.52	13.99	14.46	14.94
Linear Speed mm/s	Lead 6										340	300	260	230	210	180	160	150	130	120	110	100	90	
	Lead 12										680	600	520	460	420	360	320	300	260	240	220	200	180	
	Lead 24										1360	1200	1040	920	840	720	640	600	520	480	440	400	360	



Download at www.toyorobot.com


BL Motor Left Side (Sensor on the left side)

Unit : mm



BL Motor Left Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210
L	303.5	353.5	403.5	453.5	503.5	553.5	603.5	653.5	703.5	753.5	803.5	853.5	903.5	953.5	1003.5	1053.5	1103.5	1153.5	1203.5	1253.5	1303.5	1353.5	1403.5	1453.5
A	90	20	70	120	50	100	30	80	130	60	110	40	90	20	70	120	50	100	30	80	130	60	110	40
M	1	2	2	2	3	3	4	4	4	5	5	6	6	7	7	7	8	8	9	9	10	10	11	11
N	4	6	6	6	8	8	10	10	10	12	12	14	14	16	16	16	18	18	20	20	20	22	22	24
KG	4.58	5.06	5.53	6	6.48	6.95	7.42	7.89	8.37	8.84	9.31	9.78	10.25	10.73	11.2	11.67	12.15	12.62	13.09	13.56	14.04	14.51	14.98	15.45
Linear Speed mm/s	Lead 6										340	300	260	230	210	180	160	150	130	120	110	100	90	
	Lead 12										680	600	520	460	420	360	320	300	260	240	220	200	180	
	Lead 24										1360	1200	1040	920	840	720	640	600	520	480	440	400	360	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-14 1-axis


► Ball Screw Drive



Download at www.toyorobot.com


BR Motor Right Side (Sensor on the left side)

Unit : mm




BR Motor Right Side (Sensor on the right side)

Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210
L	303.5	353.5	403.5	453.5	503.5	553.5	603.5	653.5	703.5	753.5	803.5	853.5	903.5	953.5	1003.5	1053.5	1103.5	1153.5	1203.5	1253.5	1303.5	1353.5	1403.5	1453.5
A	90	20	70	120	50	100	30	80	130	60	110	40	90	20	70	120	50	100	30	80	130	60	110	40
M	1	2	2	2	3	3	4	4	4	5	5	6	6	7	7	7	8	8	9	9	9	10	10	11
N	4	6	6	6	8	8	10	10	10	12	12	14	14	16	16	16	18	18	20	20	20	22	22	24
KG	4.58	5.06	5.53	6	6.48	6.95	7.42	7.89	8.37	8.84	9.31	9.78	10.25	10.73	11.2	11.67	12.15	12.62	13.09	13.56	14.04	14.51	14.98	15.45
Linear Speed mm/s	Lead 6										340	300	260	230	210	180	160	150	130	120	110	100	90	
	Lead 12										680	600	520	460	420	360	320	300	260	240	220	200	180	
	Lead 24										1360	1200	1040	920	840	720	640	600	520	480	440	400	360	



Download at www.toyorobot.com


BM Motor Bottom Side (Sensor on the left side)

Unit: mm



BM Motor Bottom Side (Sensor on the right side)

Unit: mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210
L	315	365	415	465	515	565	615	665	715	765	815	865	915	965	1015	1065	1115	1165	1215	1265	1315	1365	1415	1465
A	90	20	70	120	50	100	30	80	130	60	110	40	90	20	70	120	50	100	30	80	130	60	110	40
M	1	2	2	2	3	3	4	4	4	5	5	6	6	7	7	7	8	8	9	9	9	10	10	11
N	4	6	6	6	8	8	10	10	10	12	12	14	14	16	16	16	18	18	20	20	20	22	22	24
KG	4.58	5.06	5.53	6	6.48	6.95	7.42	7.89	8.37	8.84	9.31	9.78	10.25	10.73	11.2	11.67	12.15	12.62	13.09	13.56	14.04	14.51	14.98	15.45
Linear Speed mm/s	Lead 6										340	300	260	230	210	180	160	150	130	120	110	100	90	
	Lead 12										680	600	520	460	420	360	320	300	260	240	220	200	180	
	Lead 24										1360	1200	1040	920	840	720	640	600	520	480	440	400	400	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-17 1-axis

► Ball Screw Drive

精度
±0.005 mm



Max. stroke 1500mm

Max. Speed 2400mm/s

Motor Output 400W

Ball Screw ø20mm

Linear Guide 15X12.5-2pcs

Ordering Method

ETH2-17 - L5 - 500 - BC - T40B - C3N5L - Refer to the right page. - 0001

Model Options Customization Order No.

Stroke
50-1500mm
50 mm Pitch

Ball Screw Lead

5	5mm
10	10mm
20	20mm
40	40mm

Motor Position

BC	Motor Exposed
BL	Motor Left Side
BR	Motor Right Side
BM	Motor Bottom Side

Motor Brand & Power Output

M	Mitsubishi	10	-	B
P	Panasonic	20	-	
Y	Yaskawa	40	400W	
T	Delta	75	-	

Home Sensor

Out Side	
C	Motor Side
D	Opposite Motor Side
No Sensor	
E	No Sensor

Limit Sensor

Out Side	
3	1 Pc
4	2 Pcs
6	3 Pcs
7	4 Pcs
8	5 Pcs
9	6 Pcs
No Sensor	
5	No Sensor

Output type & Cable length


N5	NPN+5M Cable
P2	PNP+2M Cable
P5	PNP+5M Cable
-	NPN+2M Cable

Sensor location

L	Left side
R	Right side

Refer to the right page.

*When the stroke is 50mm, Home + limit sensors is 2 maximum (only C3/D3/E3/E4/E5 can be selected)




Specification

Performance	Repeatability		mm	±0.005							
	Lead		mm	5		10		20		40	
	Maximum Rotating speed		rpm	3600	3000	3600	3000	3600	3000	3600	3000
	Maximum linear speed ※1		mm/s	300	250	600	500	1200	1000	2400	2000
	Maximum Payload	Horizontal	kg	120	120	110	110	75	85	15	22
		Vertical (No regenerative resistor)	kg	40	50	24	26	10	11	9	10
		Vertical (External 200W regenerative resistor)	kg	50	50	30	30	17	17	15	15
	Rated Thrust		N	1356		678		339		170	
	Stroke (increments)		mm	50-1500mm/(50 increments)							
	Maximum acceleration		G	0.15	0.13	0.31	0.25	0.61	0.51	1.22	1.02
	Ball screw	Basic dynamic load rating Ca	N	17795		10295		5414		6406	
		Basic static load rating Coa	N	45617		22964		10877		15667	
	Linear Guide	Dynamic horizontal (100km)	N	29573							
		Static Horizontal	N	63504							
	Fixed bearing	Basic dynamic load rating Cr	N	9666							
Static load rating Cor		N	6400								
Parts	AC Servo Motor Output		W	400							
	Ball Screw Ø		mm	C7Ø20							
	High Rigidity Linear Guide		mm	W15XH12.5							
	Coupling		mm	14X12							
	Home Sensor	Outside		T64N2(NPN)							


※1 During in a long stroke, it causes ballscrew deflection, the speed must reduce. (Please refer to the linear velocity from the data sheet below the dimension graph.)

Allowable Overhang




(Unit: mm)

Horizontal Installation		A	B	C
Lead 5	70kg	2782	165	155
	90kg	2077	116	109
	120kg	1452	74	70
Lead 10	65kg	1010	154	138
	85kg	728	106	95
	110kg	516	70	63
Lead 20	55kg	332	132	99
	75kg	219	83	63
	85kg	181	67	51
Lead 40	10kg	558	613	296
	15kg	358	391	189
	22kg	230	250	121



(Unit: mm)


Wall Installation		A	B	C
Lead 5	70kg	155	165	2782
	90kg	109	116	2077
	120kg	70	74	1452
Lead 10	65kg	138	154	1010
	85kg	95	106	728
	110kg	63	70	516
Lead 20	55kg	99	132	332
	75kg	63	83	219
	85kg	51	67	181
Lead 40	10kg	296	613	558
	15kg	189	391	358
	22kg	121	250	230



(Unit: mm)

Vertical Installation		A	C
Lead 5	30kg	483	483
	40kg	362	362
	50kg	290	290
Lead 10	24kg	508	508
	26kg	469	469
	30kg	406	406
Lead 20	10kg	806	806
	11kg	733	733
	17kg	474	474
Lead 40	9kg	420	420
	10kg	378	378
	15kg	252	252

Static Loading Moment



(Unit: N.m)

MY	680
MP	680
MR	537

* The data represented by the moment table is the center of gravity of the load. The length of the overhang is allowed in a single direction.

* Operation life is 10,000km when the product is using under the specified conditions.

* Data information is not for ceiling-mount inverse use.

Contact us for the details if you want to apply ceiling-mount inverse usage.

* The life and torque are calculated by setting the motor acceleration and deceleration for 0.2 seconds.

Options

P - MM - CMK

Standard PIN hole		
Code	Instructions	Refer to
P	Standard PIN hole	P.677

Selectable Cable Leading Direction		
Code	Instructions	Refer to
MW	Upper side	P.679 ~ P.680
MM	Bottom side	
ML	Left side	
MR	Right side	

Additional keyway for motor drive parts				
Code	Instructions			Refer to
	Keyway Groove	Motor Position	Shipment Type	
CMK	Single (Limited to the motor side)	BC/M	Keyway Coupling	P.681 ~ P.682
		BL/BR/BM	Keyway Belt Pulley	
SKY	Double	BC/M	Keyway Coupling	
		BL/BR/BM	Keyway Belt Pulley	
SKN	Double	BC/M	Without Coupling (Please purchase and install by yourself)	
		BL/BR/BM	Without Belt Pulley (Please purchase and install by yourself)	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D


ETH2-22D

ETH2-30D


▶ Ball Screw Drive



Unit: mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510
L	315	365	415	465	515	565	615	665	715	765	815	865	915	965	1015	1065	1115	1165	1215	1265	1315	1365	1415	1465	1515	1565	1615	1665	1715	1765
A	129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	9	69	119	49	99	29	79	129	59	109	39	89	19
M	1	2	2	3	3	4	4	4	5	5	6	6	6	7	7	8	8	9	9	9	10	10	11	11	11	12	12	13	13	14
N	4	6	6	8	8	10	10	10	12	12	14	14	14	16	16	18	18	20	20	20	22	22	24	24	24	26	26	28	28	30
KG	5.94	6.52	7.1	7.68	8.26	8.84	9.42	9.99	10.58	11.15	11.74	12.31	12.9	13.47	14.05	14.63	15.21	15.79	16.37	16.95	17.53	18.11	18.69	19.27	19.85	20.43	21	21.59	22.16	22.75
Linear Speed mm/s	Lead 5	300												275 250 225 200 183 167 150 142 133 117 108 100 92 83 75																
	Lead 10	600												550 500 450 400 367 333 300 283 267 233 217 200 183 167 150																
	Lead 20	1200												1100 1000 900 800 733 667 600 567 533 467 433 400 367 333 300																
	Lead 40	2400												2200 2000 1800 1600 1467 1333 1200 1133 1067 933 867 800 733 667 600																



Download at www.toyorobot.com


BL Motor Left Side (Sensor on the left side)

Unit : mm



BL Motor Left Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	
L	342	392	442	492	542	592	642	692	742	792	842	892	942	992	1042	1092	1142	1192	1242	1292	1342	1392	1442	1492	1542	1592	1642	1692	1742	1792	
A	129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	19	
M	1	2	2	3	3	4	4	4	5	5	6	6	6	7	7	8	8	9	9	9	10	10	11	11	11	12	12	13	13	14	
N	4	6	6	8	8	10	10	10	12	12	14	14	14	16	16	18	18	20	20	20	22	22	24	24	24	26	26	28	28	30	
KG	6.54	7.12	7.7	8.28	8.86	9.44	10.02	10.6	11.18	11.76	12.34	12.92	13.5	14.08	14.65	15.24	15.81	16.4	16.97	17.55	18.13	18.71	19.29	19.87	20.45	21.03	21.61	22.19	22.77	23.35	
Linear Speed mm/s	Lead 5	300												275	250	225	200	183	167	150	142	133	117	108	100	92	83	75			
	Lead 10	600												550	500	450	400	367	333	300	283	267	233	217	200	183	167	150			
	Lead 20	1200												1100	1000	900	800	733	667	600	567	533	467	433	400	367	333	300			
	Lead 40	2400												2200	2000	1800	1600	1467	1333	1200	1133	1067	933	867	800	733	667	600			

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-17 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com •


BR Motor Right Side (Sensor on the left side)

Unit : mm




BR Motor Right Side (Sensor on the right side)

Unit : mm




Stroke		50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500																																																																																																																																																																		
Limit Stroke (±1)		60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510																																																																																																																																																																		
L		342	392	442	492	542	592	642	692	742	792	842	892	942	992	1042	1092	1142	1192	1242	1292	1342	1392	1442	1492	1542	1592	1642	1692	1742	1792																																																																																																																																																																		
A		129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	19																																																																																																																																																																		
M		1	2	2	3	3	4	4	4	5	5	6	6	6	7	7	8	8	9	9	9	10	10	11	11	11	12	12	13	13	14																																																																																																																																																																		
N		4	6	6	8	8	10	10	10	12	12	14	14	14	16	16	18	18	20	20	20	22	22	24	24	24	26	26	28	28	30																																																																																																																																																																		
KG		6.54	7.12	7.7	8.28	8.86	9.44	10.02	10.6	11.18	11.76	12.34	12.92	13.5	14.08	14.65	15.24	15.81	16.4	16.97	17.55	18.13	18.71	19.29	19.87	20.45	21.03	21.61	22.19	22.77	23.35																																																																																																																																																																		
Linear Speed mm/s	Lead 5	300												275												225												200												183												167												150												142												133												117												108												100												92												83												75																							
	Lead 10	600												550												500												450												400												367												333												300												283												267												233												217												200												183												167												150											
	Lead 20	1200												1100												1000												900												800												733												667												600												567												533												467												433												400												367												333												300											
	Lead 40	2400												2200												2000												1800												1600												1467												1333												1200												1133												1067												933												867												800												733												667												600											



Download at www.toyorobot.com


BM Motor Bottom Side (Sensor on the left side)

Unit : mm



BM Motor Bottom Side (Sensor on the left side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510
L	355	405	455	505	555	605	655	705	755	805	855	905	955	1005	1055	1105	1155	1205	1255	1305	1355	1405	1455	1505	1555	1605	1655	1705	1755	1805
A	129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	19
M	1	2	2	3	3	4	4	4	5	5	6	6	6	7	7	8	8	9	9	9	10	10	11	11	11	12	12	13	13	14
N	4	6	6	8	8	10	10	10	12	12	14	14	14	16	16	18	18	20	20	20	22	22	24	24	24	26	26	28	28	30
KG	6.54	7.12	7.7	8.28	8.86	9.44	10.02	10.6	11.18	11.76	12.34	12.92	13.5	14.08	14.65	15.24	15.81	16.4	16.97	17.55	18.13	18.71	19.29	19.87	20.45	21.03	21.61	22.19	22.77	23.35
Linear Speed mm/s	Lead 5	300												275	250	225	200	183	167	150	142	133	117	108	108	92	83	75		
	Lead 10	600												550	500	450	400	367	333	300	283	267	233	217	200	183	167	150		
	Lead 20	1200												1100	1000	900	800	733	667	600	567	533	467	433	400	367	333	300		
	Lead 40	2400												2200	2000	1800	1600	1467	1333	1200	1133	1067	933	867	800	733	667	600		

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-22 1-axis

▶ Ball Screw Drive

精度
±0.005 mm



Max. stroke 1800mm

Max. Speed 1500mm/s

Motor Output 750W

Ball Screw ø25mm

Linear Guide 20X16.3-2pcs

Ordering Method


ETH2-22 - L5 - 500 - BC - T75B - C3N5L - Refer to the right page. - 0001

Model Options Customization Order No.

<

*If No Brake, No Description.

*When the stroke is 50mm, Home + limit sensors is 2 maximum (only C3/D3/E3/E4/E5 can be selected)




Specification

Performance	Repeatability		mm	±0.005					
	Lead		mm	5		10		25	
	Maximum Rotating speed		rpm	3600	3000	3600	3000	3600	3000
	Maximum linear speed ※1		mm/s	300	250	600	500	1500	1250
	Maximum Payload	Horizontal (No regenerative resistor)	kg	150	150	150	150	40	80
		Horizontal (External 200W regenerative resistor)	kg	-	-	-	-	100	105
		Vertical (No regenerative resistor)	kg	55	60	30	33	13	15
		Vertical (External 200W regenerative resistor)	kg	60	65	35	38	18	23
	Rated Thrust		N	2553		1276		511	
	Stroke (increments)		mm	50-1800mm/(50 increments)					
	Maximum acceleration		G	0.15	0.13	0.31	0.25	0.76	0.64
	Ball screw	Basic dynamic load rating Ca	N	11116		16069		8270	
		Basic static load rating Coa	N	27338		45450		21572	
	Linear Guide	Dynamic horizontal (100km)	N	45517					
		Static Horizontal	N	98820					
Fixed bearing	Basic dynamic load rating Cr	N	22093						
	Static load rating Cor	N	15100						
Parts	AC Servo Motor Output		W	750					
	Ball Screw Ø		mm	C7Ø25					
	High Rigidity Linear Guide		mm	W20XH16.3					
	Coupling		mm	19X17					
	Home Sensor	Outside		T64N2(NPN)					


※1 During in a long stroke, it causes ballscrew deflection, the speed must reduce. (Please refer to the linear velocity from the data sheet below the dimension graph.)

Allowable Overhang




(Unit: mm)

Horizontal Installation	A	B	C
Lead 5	100kg	4520	264
	125kg	3505	196
	150kg	2824	151
Lead 10	100kg	1512	225
	125kg	1155	165
	150kg	914	125
Lead 25	40kg	721	398
	80kg	309	161
	105kg	209	105



(Unit: mm)


Wall Installation	A	B	C
Lead 5	100kg	258	264
	125kg	191	196
	150kg	147	151
Lead 10	100kg	210	225
	125kg	154	165
	150kg	116	125
Lead 25	40kg	279	398
	80kg	114	161
	105kg	75	105



(Unit: mm)

Vertical Installation	A	C
Lead 5	55kg	591
	62kg	524
	65kg	500
Lead 10	30kg	915
	33kg	832
	38kg	722
Lead 25	13kg	1087
	18kg	785
	23kg	614

Static Loading Moment



(Unit: N.m)

MY	1538
MP	1538
MR	1263

* The data represented by the moment table is the center of gravity of the load. The length of the overhang is allowed in a single direction.

* Operation life is 10,000km when the product is using under the specified conditions.

* Data information is not for ceiling-mount inverse use. Contact us for the details if you want to apply ceiling-mount inverse usage.

* The life and torque are calculated by setting the motor acceleration and deceleration for 0.2 seconds.

Options

P

MM

CMK

Standard PIN hole		
Code	Instructions	Refer to
P	Standard PIN hole	P.677

Selectable Cable Leading Direction		
Code	Instructions	Refer to
MW	Upper side	P.679 ~ P.680
MM	Bottom side	
ML	Left side	
MR	Right side	

Additional keyway for motor drive parts				
Code	Keyway Groove	Motor Position	Instructions	
			Shipment Type	Refer to
CMK	Single (Limited to the motor side)	BC/M	Keyway Coupling	P.681 ~ P.682
		BL/BR/BM	Keyway Belt Pulley	
SKY	Double	BC/M	Keyway Coupling	
		BL/BR/BM	Keyway Belt Pulley	
SKN	Double	BC/M	Without Coupling (Please purchase and install by yourself)	
		BL/BR/BM	Without Belt Pulley (Please purchase and install by yourself)	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-22 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com •


BC Motor Exposed (Sensor on the left side)

Unit : mm




BC Motor Exposed (Sensor on the right side)

Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750	1800
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760	1810
L	393.5	443.5	493.5	543.5	593.5	643.5	693.5	743.5	793.5	843.5	893.5	943.5	993.5	1043.5	1093.5	1143.5	1193.5	1243.5	1293.5	1343.5	1393.5	1443.5	1493.5	1543.5	1593.5	1643.5	1693.5	1743.5	1793.5	1843.5	1893.5	1943.5	1993.5	2043.5	2093.5	2143.5
A	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21
M	2	2	3	3	4	4	5	5	5	6	6	7	7	7	8	8	9	9	10	10	10	11	11	12	12	12	13	13	14	14	15	15	15	16	16	17
N	6	6	8	8	10	10	12	12	12	14	14	16	16	16	18	18	20	20	22	22	22	24	24	26	26	26	28	28	30	30	32	32	32	34	34	36
KG	11.99	12.92	13.86	14.79	15.73	16.66	17.6	18.53	19.46	20.4	21.33	22.27	23.2	24.14	25.07	26.01	26.94	27.88	28.81	29.75	30.68	31.62	32.55	33.49	34.42	35.35	36.29	37.22	38.16	39.09	40.03	40.96	41.89	42.83	43.76	44.7
Linear Speed mm/s	Lead 5	300														275	250	233	208	192	175	167	150	142	133	125	117	108	100	92	83	75	67			
	Lead 10	600														550	500	467	417	383	350	333	300	283	267	250	233	217	200	183	167	150	133			
	Lead 25	1500														1375	1250	1167	1042	958	875	833	750	708	667	625	583	542	500	458	417	375	333			



Download at www.toyorobot.com


BL Motor Left Side (Sensor on the left side)

Unit : mm



BL Motor Left Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750	1800
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760	1810
L	437.5	487.5	537.5	587.5	637.5	687.5	737.5	787.5	837.5	887.5	937.5	987.5	1037.5	1087.5	1137.5	1187.5	1237.5	1287.5	1337.5	1387.5	1437.5	1487.5	1537.5	1587.5	1637.5	1687.5	1737.5	1787.5	1837.5	1887.5	1937.5	1987.5	2037.5	2087.5	2137.5	2187.5
A	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21
M	2	2	3	3	4	4	5	5	5	6	6	7	7	7	8	8	9	9	10	10	10	10	11	11	12	12	12	13	13	14	14	15	15	16	16	17
N	6	6	8	8	10	10	12	12	12	14	14	16	16	16	18	18	20	20	22	22	22	24	24	26	26	26	28	28	30	30	32	32	32	34	34	36
KG	13.07	14	14.94	15.87	16.81	17.74	18.68	19.61	20.54	21.48	22.41	23.35	24.28	25.21	26.15	27.08	28.02	28.95	29.89	30.82	31.75	32.69	33.62	34.56	35.49	36.42	37.36	38.29	39.23	40.16	41.1	42.03	42.97	43.9	44.84	45.77
Linear Speed mm/s	Lead 5	300														275	250	233	208	192	175	167	150	142	133	125	117	108	100	92	83	75	67			
	Lead 10	600														550	500	467	417	383	350	333	300	283	267	250	233	217	200	183	167	150	133			
	Lead 25	1500														1375	1250	1167	1042	958	875	833	750	708	667	625	583	542	500	458	417	375	333			

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D


ETH2-30D



Download at www.toyorobot.com


BR Motor Right Side (Sensor on the left side)

Unit : mm




BR Motor Right Side (Sensor on the right side)

Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750	1800
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760	1810
L	437.5	487.5	537.5	587.5	637.5	687.5	737.5	787.5	837.5	887.5	937.5	987.5	1037.5	1087.5	1137.5	1187.5	1237.5	1287.5	1337.5	1387.5	1437.5	1487.5	1537.5	1587.5	1637.5	1687.5	1737.5	1787.5	1837.5	1887.5	1937.5	1987.5	2037.5	2087.5	2137.5	2187.5
A	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21
M	2	2	3	3	4	4	5	5	5	6	6	7	7	7	8	8	9	9	10	10	10	11	11	12	12	12	13	13	14	14	15	15	15	16	16	17
N	6	6	8	8	10	10	12	12	12	14	14	16	16	16	18	18	20	20	22	22	22	24	24	26	26	26	28	28	30	30	32	32	32	34	34	36
KG	13.07	14	14.94	15.87	16.81	17.74	18.68	19.61	20.54	21.48	22.41	23.35	24.28	25.21	26.15	27.08	28.02	28.95	29.89	30.82	31.75	32.69	33.62	34.56	35.49	36.42	37.36	38.29	39.23	40.16	41.1	42.03	42.97	43.9	44.84	45.77
Linear Speed mm/s	Lead 5	300														275	250	233	208	192	175	167	150	142	133	125	117	108	100	92	83	75	67			
	Lead 10	600														550	500	467	417	383	350	333	300	283	267	250	233	217	200	183	167	150	133			
	Lead 25	1500														1375	1250	1167	1042	958	875	833	750	708	667	625	583	542	500	458	417	375	333			



Download at www.toyorobot.com


BM Motor Bottom Side (Sensor on the left side)

Unit : mm



BM Motor Bottom Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750	1800
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760	1810
L	451.5	501.5	551.5	601.5	651.5	701.5	751.5	801.5	851.5	901.5	951.5	1001.5	1051.5	1101.5	1151.5	1201.5	1251.5	1301.5	1351.5	1401.5	1451.5	1501.5	1551.5	1601.5	1651.5	1701.5	1751.5	1801.5	1851.5	1901.5	1951.5	2001.5	2051.5	2101.5	2151.5	2201.5
A	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21
M	2	2	3	3	4	4	5	5	5	6	6	7	7	7	8	8	9	9	10	10	10	11	11	12	12	13	13	14	14	15	15	16	16	17	17	
N	6	6	8	8	10	10	12	12	12	14	14	16	16	16	18	18	20	20	22	22	22	24	24	26	26	26	28	28	30	30	32	32	32	34	34	36
KG	13.07	14	14.94	15.87	16.81	17.74	18.68	19.61	20.54	21.48	22.41	23.35	24.28	25.21	26.15	27.08	28.02	28.95	29.89	30.82	31.75	32.69	33.62	34.56	35.49	36.42	37.36	38.29	39.23	40.16	41.1	42.03	42.97	43.9	44.84	45.77
Linear Speed mm/s	Lead 5	300														275	250	233	208	192	175	167	150	142	133	125	117	108	100	92	83	75	67			
	Lead 10	600														550	500	467	417	383	350	333	300	283	267	250	233	217	200	183	167	150	133			
	Lead 25	1500														1375	1250	1167	1042	958	875	833	750	708	667	625	583	542	500	458	417	375	333			

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-30 1-axis

▶ Ball Screw Drive

精度
±0.005 mm



Max. stroke 2100mm

Max. Speed 1280mm/s

Motor Output 1500W

Ball Screw ø32mm

Linear Guide 23X19.2-2pcs

Ordering Method

ETH2-30 - L10 - 500 - BC - T150B - C3N5L - 0001

Model

Refer to the right page.

Options

Customization Order No.

Stroke

50-2100mm
50 mm Pitch

Motor Position

BC	Motor Exposed
BL	Motor Left Side
BR	Motor Right Side
BM	Motor Bottom Side

Motor Brand & Power Output

M	Mitsubishi	40	-	B
P	Panasonic	75	-	
T	Delta	150	1500W	

*If No Brake, No Description.

Home Sensor

Out Side	
C	Motor Side
D	Opposite Motor Side
No Sensor	
E	No Sensor

Limit Sensor

Out Side	
3	1 Pc
4	2 Pcs
6	3 Pcs
7	4 Pcs
8	5 Pcs
9	6 Pcs
No Sensor	
5	No Sensor


*When the stroke is 50mm, Home + limit sensors is 2 maximum (only C3/D3/E3/E4/E5 can be selected)

Sensor location

L	Left side
R	Right side

Output type & Cable length

N5	NPN+5M Cable
P2	PNP+2M Cable
P5	PNP+5M Cable
-	NPN+2M Cable




Specification


Performance	Repeatability		mm	±0.005		
	Lead		mm	10	20	32
	Maximum Rotating speed		rpm	2400	2400	2400
	Maximum linear speed ※1		mm/s	400	800	1280
	Maximum Payload	Horizontal (No regenerative resistor)	kg	250	200	20
		Horizontal (External 200W regenerative resistor)	kg	-	-	105
		Vertical (No regenerative resistor)	kg	35	20	10
		Vertical (External 200W regenerative resistor)	kg	48	25	12
	Rated Thrust		N	3824	1912	1195
	Stroke (increments)		mm	50-2100mm/(50 increments)		
	Maximum acceleration		G	0.20	0.41	0.65
	Ball screw	Basic dynamic load rating Ca	N	47137	18708	18031
		Basic static load rating Coa	N	119760	53778	52277
Parts	Linear Guide	Dynamic horizontal (100km)	N	85033		
		Static Horizontal	N	177552		
	Fixed bearing	Basic dynamic load rating Cr	N	25017		
		Static load rating Cor	N	18940		
	AC Servo Motor Output		W	1500		
	Ball Screw Ø		mm	C7Ø32		
Parts	High Rigidity Linear Guide		mm	W23XH19.2		
	Coupling		mm	24X22		
	Home Sensor		Outside	T64N2(NPN)		

※1 During in a long stroke, it causes ballscrew deflection, the speed must reduce. (Please refer to the linear velocity from the data sheet below the dimension graph.)


Allowable Overhang



(Unit : mm)



(Unit : mm)




(Unit : mm)

Horizontal Installation		A	B	C
Lead 10	100kg	5800	457	650
	200kg	2730	196	279
	250kg	2110	144	205
Lead 20	50kg	4005	829	1075
	100kg	1922	382	497
	200kg	876	159	208
Lead 32	20kg	4190	1655	1790
	50kg	1617	625	679
	105kg	716	262	289

Wall Installation		A	B	C
Lead 10	100kg	650	457	5800
	200kg	279	196	2730
	250kg	205	144	2110
Lead 20	50kg	1075	829	4005
	100kg	497	382	1922
	200kg	208	159	876
Lead 32	20kg	1790	1655	4190
	50kg	679	625	1617
	105kg	289	262	716

Vertical Installation		A	C
Lead 10	25kg	2009	2009
	35kg	1435	1435
	48kg	1046	1046
Lead 20	20kg	2052	2052
	25kg	1642	1642
	-	-	-
Lead 32	10kg	2919	2919
	12kg	2433	2433
	-	-	-

Static Loading Moment



(Unit : N.m)

MY	2371
MP	2371
MR	2874

* The data represented by the moment table is the center of gravity of the load. The length of the overhang is allowed in a single direction.

* Operation life is 10,000km when the product is using under the specified conditions.

* Data information is not for ceiling-mount inverse use. Contact us for the details if you want to apply ceiling-mount inverse usage.

* The life and torque are calculated by setting the motor acceleration and deceleration for 0.2 seconds.

Options

P

MM

CMK

Standard PIN hole		
Code	Instructions	Refer to
P	Standard PIN hole	P.677

Selectable Cable Leading Direction		
Code	Instructions	Refer to
MW	Upper side	P.679 ~ P.680
MM	Bottom side	
ML	Left side	
MR	Right side	

Additional keyway for motor drive parts				
Code	Keyway Groove	Motor Position	Shipment Type	Refer to
CMK	Single (Limited to the motor side)	BC/M	Keyway Coupling	P.681 ~ P.682
		BL/BR/BM	Keyway Belt Pulley	
SKY	Double	BC/M	Keyway Coupling	
		BL/BR/BM	Keyway Belt Pulley	
SKN	Double	BC/M	Without Coupling (Please purchase and install by yourself)	
		BL/BR/BM	Without Belt Pulley (Please purchase and install by yourself)	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D


ETH2-30D



Download at www.toyorobot.com


BC Motor Exposed (Sensor on the left side)

Unit : mm



BC Motor Exposed (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310
L	443.5	493.5	543.5	593.5	643.5	693.5	743.5	793.5	843.5	893.5	943.5	993.5	1043.5	1093.5	1143.5	1193.5	1243.5	1293.5	1343.5	1393.5	1443.5	1493.5	1543.5	1593.5	1643.5	1693.5
A	21	71	121	171	221	271	321	371	421	471	521	571	621	671	721	771	821	871	921	971	1021	1071	1121	1171	1221	1271
M	3	3	3	4	4	5	5	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13
N	8	8	8	10	10	12	12	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28
KG	23.24	24.76	26.32	27.86	29.41	30.96	32.51	34.06	35.61	37.15	38.71	40.25	41.81	43.35	44.91	46.45	47.99	49.55	51.09	52.65	54.19	55.74	57.29	58.84	60.39	61.94
Linear Speed mm/s	Lead 10		400																							
	Lead 20		800																							
	Lead 32		1280																							


Stroke	1350	1400	1450	1500	1550	1600	1650	1700	1750	1800	1850	1900	1950	2000	2050	2100
Limit Stroke (±1)	1360	1410	1460	1510	1560	1610	1660	1710	1760	1810	1860	1910	1960	2010	2060	2110
L	1743.5	1793.5	1843.5	1893.5	1943.5	1993.5	2043.5	2093.5	2143.5	2193.5	2243.5	2293.5	2343.5	2393.5	2443.5	2493.5
A	121	51	101	151	201	251	301	351	401	451	501	551	601	651	701	751
M	13	14	14	15	15	16	16	17	17	18	18	18	19	19	20	20
N	28	30	30	32	32	34	34	36	36	38	38	38	40	40	42	42
KG	63.49	65.04	66.58	68.14	69.68	71.24	72.78	74.32	75.88	77.42	78.98	80.52	82.08	83.62	85.17	86.72
Linear Speed mm/s	Lead 10		383	367	333	317	300	283	267	250	233	217	200	183	167	
	Lead 20		767	733	667	633	600	567	533	500	467	433	400	367	333	
	Lead 32		1227	1173	1067	1013	960	907	853	800	747	693	640	587	533	



• Download at www.toyorobot.com •


BL Motor Left Side (Sensor on the left side)

Unit: mm



BL Motor Left Side (Sensor on the right side)

Unit : mm

[illegible]

Stroke	1350	1400	1450	1500	1550	1600	1650	1700	1750	1800	1850	1900	1950	2000	2050	2100
Limit Stroke (±1)	1360	1410	1460	1510	1560	1610	1660	1710	1760	1810	1860	1910	1960	2010	2060	2110
L	1760	1810	1860	1910	1960	2010	2060	2110	2160	2210	2260	2310	2360	2410	2460	2510
A	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31
M	13	14	14	15	15	15	16	16	17	17	18	18	18	19	19	20
N	28	30	30	32	32	32	34	34	36	36	38	38	38	40	40	42
KG	65.82	67.36	68.91	70.46	72.01	73.56	75.11	76.65	78.21	79.75	81.31	82.85	84.41	85.95	87.49	89.05
Linear Speed mm/s	Lead 10	383	367	333	317	300	283	267	250	233	217	200	183	167		
	Lead 20	767	733	667	633	600	567	533	500	467	433	400	367	333		
	Lead 32	1227	1173	1067	1013	960	907	853	800	747	693	640	587	533		

Features

Standard Ball Screw Type

Multi Axis Type
XYGT/XYTH/XYTE

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

FTH2-141

FTH2-17M

FTH2-22


ETH2-30



• Download at www.toyorobot.com •


BR Motor Right Side (Sensor on the left side)

Unit: mm



BR Motor Right Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	
L	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	
A	21	71	121	151	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	
M	3	3	3	4	4	5	5	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13	
N	8	8	8	10	10	12	12	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28	
KG	25.56	27.09	28.65	30.19	31.73	33.29	34.83	36.39	37.93	39.48	41.03	42.58	44.13	45.68	47.23	48.78	50.32	51.88	53.42	54.98	56.52	58.06	59.62	61.16	62.72	64.28	
Linear Speed mm/s	Lead 10	400																									
	Lead 20	800																									
	Lead 32	1280																									

Stroke	1350	1400	1450	1500	1550	1600	1650	1700	1750	1800	1850	1900	1950	2000	2050	2100
Limit Stroke (±1)	1360	1410	1460	1510	1560	1610	1660	1710	1760	1810	1860	1910	1960	2010	2060	2110
L	1760	1810	1860	1910	1960	2010	2060	2110	2160	2210	2260	2310	2360	2410	2460	2510
A	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31
M	13	14	14	15	15	15	16	16	17	17	18	18	18	19	19	20
N	28	30	30	32	32	32	34	34	36	36	38	38	38	40	40	42
KG	65.82	67.36	68.91	70.46	72.01	73.56	75.11	76.65	78.21	79.75	81.31	82.85	84.41	85.95	87.49	89.05
Linear Speed mm/s	Lead 10	383	367	333	317	300	283	267	250	233	217	200	183	167		
	Lead 20	767	733	667	633	600	567	533	500	467	433	400	367	333		
	Lead 32	1227	1173	1067	1013	960	907	853	800	747	693	640	587	533		

ETH2-30 1-axis

▶ Ball Screw Drive

精度
±0.005 mm



Max. stroke 2100mm

Max. Speed 640mm/s

Motor Output 750W

Ball Screw ø32mm

Linear Guide 23X19.2-2pcs

* Differ from different gear ratio.

Ordering Method

ETH2-30 - L10 - 500 - BC - T75B - C3N5L - 03 - Refer to the right page. - 0001

Model

Options Customization Order No.

Stroke

50-2100mm
50 mm Pitch

Sensor location

L Left side
R Right side

Slide

3 3:1
5 5:1

Ball Screw Lead

10	10mm
20	20mm
32	32mm

Motor Position

BC	Motor Exposed
BL	Motor Left Side
BR	Motor Right Side
BM	Motor Bottom Side

Motor Brand & Power Output

M	Mitsubishi	10	-	B
P	Panasonic	20	-	
Y	Yaskawa	40	-	
T	Delta	75	750W	

* If No Brake, No Description.

Home Sensor

	Out Side
C	Motor Side
D	Opposite Motor Side
	No Sensor
E	No Sensor


Limit Sensor

	Out Side
3	1 Pc
4	2 Pcs
6	3 Pcs
7	4 Pcs
8	5 Pcs
9	6 Pcs
	No Sensor
5	No Sensor

Output type & Cable length

N5	NPN+5M Cable
P2	PNP+2M Cable
P5	PNP+5M Cable
-	NPN+2M Cable

*When the stroke is 50mm, Home + limit sensors is 2 maximum (only C3/D3/E3/E4/E5 can be selected)




Specification

Performance	Repeatability		mm	±0.005					
	Lead		mm	10		20		32	
	Reduce Ratio			3:1	5:1	3:1	5:1	3:1	5:1
	Maximum Rotating speed		rpm	3600		3600		3600	
	Maximum linear speed ※1		mm/s	200	120	400	240	640	384
	Maximum Payload	Horizontal	kg	400	400	300	300	180	180
		Vertical (No regenerative resistor)	kg	110	155	55	75	20	38
		Vertical (External 200W regenerative resistor)	kg	130	200	65	110	38	60
	Rated Thrust		N	3829	6382	1915	3191	1197	1994
	Stroke (increments)		mm	50-2100mm/(50 increments)					
	Maximum acceleration		G	0.10	0.06	0.20	0.12	0.33	0.20
	Ball screw	Basic dynamic load rating Ca	N	47137		18708		18031	
		Basic static load rating Coa	N	119760		53778		52277	
	Linear Guide	Dynamic horizontal (100km)	N	85033					
		Static Horizontal	N	177552					
Fixed bearing	Basic dynamic load rating Cr	N	25017						
	Static load rating Cor	N	18940						
Parts	AC Servo Motor Output		W	750					
	Ball Screw Ø		mm	C7Ø32					
	High Rigidity Linear Guide		mm	W23XH19.2					
	Coupling		mm	22X22					
	Home Sensor	Outside		T64N2(NPN)					


※1 During in a long stroke, it causes ballscrew deflection, the speed must reduce. (Please refer to the linear velocity from the data sheet below the dimension graph.)

Allowable Overhang




(Unit: mm)

Horizontal Installation		A	B	C
Lead 10	200kg	8155	233	339
	300kg	5180	134	195
	400kg	3659	84	122
Lead 20	100kg	5800	457	650
	200kg	2730	196	279
	300kg	1691	109	155
Lead 32	80kg	3518	528	716
	130kg	2086	300	408
	180kg	1447	199	270



(Unit: mm)


Wall Installation		A	B	C
Lead 10	200kg	339	233	8155
	300kg	195	134	5180
	400kg	122	84	3659
Lead 20	100kg	650	457	5800
	200kg	279	196	2730
	300kg	155	109	1691
Lead 32	80kg	716	528	3518
	130kg	408	300	2086
	180kg	270	199	1447



(Unit: mm)

Vertical Installation		A	C
Lead 10	110kg	532	532
	155kg	377	377
	200kg	292	292
Lead 20	55kg	913	913
	75kg	669	669
	110kg	456	456
Lead 32	20kg	2223	2223
	38kg	1170	1170
	60kg	741	741

Static Loading Moment



(Unit: N.m)

MY	2371
MP	2371
MR	2874

* The data represented by the moment table is the center of gravity of the load. The length of the overhang is allowed in a single direction.

* Operation life is 10,000km when the product is using under the specified conditions.

* Data information is not for ceiling-mount inverse use.

Contact us for the details if you want to apply ceiling-mount inverse usage.

* The life and torque are calculated by setting the motor acceleration and deceleration for 0.2 seconds.

Options

P - MM - CMK

Standard PIN hole		
Code	Instructions	Refer to
P	Standard PIN hole	P.677

Selectable Cable Leading Direction		
Code	Instructions	Refer to
MW	Upper side	P.679 ~ P.680
MM	Bottom side	
ML	Left side	
MR	Right side	

Additional keyway for motor drive parts				
Code	Instructions			
	Keyway Groove	Motor Position	Shipment Type	Refer to
CMK	Single (Limited to the motor side)	BC/M	Keyway Coupling	P.681 ~ P.682
		BL/BR/BM	Keyway Belt Pulley	
SKY	Double	BC/M	Keyway Coupling	
		BL/BR/BM	Keyway Belt Pulley	
SKN	Double	BC/M	Without Coupling (Please purchase and install by yourself)	
		BL/BR/BM	Without Belt Pulley (Please purchase and install by yourself)	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D


ETH2-30D



• Download at www.toyorobot.com •


BC Motor Exposed (Sensor on the left side)

Unit : mm




BC Motor Exposed (Sensor on the right side)

Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350		
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360		
L	436.5	486.5	536.5	586.5	636.5	686.5	736.5	786.5	836.5	886.5	936.5	986.5	1036.5	1086.5	1136.5	1186.5	1236.5	1286.5	1336.5	1386.5	1436.5	1486.5	1536.5	1586.5	1636.5	1686.5	1736.5		
A	21	71	121	171	221	271	321	371	421	471	521	571	621	671	721	771	821	871	921	971	1021	1071	1121	1171	1221	1271	1321		
M	3	3	3	4	4	5	5	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13	13		
N	8	8	8	10	10	12	12	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28	28		
KG	26.34	27.87	29.43	30.97	32.51	34.07	35.61	37.17	38.71	40.26	41.81	43.36	44.91	46.46	48.01	49.56	51.1	52.66	54.2	55.76	57.3	58.84	60.4	61.94	63.5	65.04	66.6		
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1																											
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1																											
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1																											


Stroke		1400	1450	1500	1550	1600	1650	1700	1750	1800	1850	1900	1950	2000	2050				2100			
Limit Stroke (±1)		1410	1460	1510	1560	1610	1660	1710	1760	1810	1860	1910	1960	2010	2060				2110			
L		1786.5	1836.5	1886.5	1936.5	1986.5	2036.5	2086.5	2136.5	2186.5	2236.5	2286.5	2336.5	2386.5	2436.5				2486.5			
A		51	101	31	81	131	61	111	41	91	21	71	121	51	101				31			
M		14	14	15	15	16	16	16	17	17	18	18	18	19	19				20			
N		30	30	32	32	32	34	34	36	36	38	38	38	40	40				42			
KG		68.14	69.69	71.24	72.79	74.34	75.89	77.43	78.99	80.53	82.09	83.63	85.19	86.73	88.27				89.83			
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1												183 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1				167 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1				
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1												367 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1				333 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1				
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1												587 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1				533 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1				

Download at www.toyorobot.com**BL Motor Left Side (Sensor on the left side)**

Unit : mm

**BL Motor Left Side (Sensor on the right side)**

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	
L	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760	
A	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	
M	3	3	3	4	4	5	5	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13	13	
N	8	8	8	10	10	12	12	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28	28	
KG	28.78	30.31	31.86	33.41	34.95	36.51	38.05	39.61	41.15	42.69	44.24	45.79	47.35	48.89	50.45	51.99	53.54	55.09	56.64	58.19	59.74	61.28	62.84	64.38	65.94	67.48	69.04	
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1																										
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1																										
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1																										


Stroke		1400	1450	1500	1550	1600	1650	1700	1750	1800	1850	1900	1950	2000	2050		2100				
Limit Stroke (±1)		1410	1460	1510	1560	1610	1660	1710	1760	1810	1860	1910	1960	2010	2060		2110				
L		1810	1860	1910	1960	2010	2060	2110	2160	2210	2260	2310	2360	2410	2460		2510				
A		51	101	31	81	131	61	111	41	91	21	71	121	51	101		31				
M		14	14	15	15	15	16	16	17	17	18	18	18	19	19		20				
N		30	30	32	32	32	34	34	36	36	38	38	38	40	40		42				
KG		70.58	72.12	73.68	75.22	76.78	78.32	79.87	81.42	82.97	84.52	86.07	87.61	89.16	90.71		92.27				
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1												183 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1				167 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1			
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1												367 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1				333 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1			
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1												537 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1				533 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1			



• Download at www.toyorobot.com •


BR Motor Right Side (Sensor on the left side)

Unit : mm



BR Motor Right Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350		
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360		
L	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760		
A	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121		
M	3	3	3	4	4	5	5	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13	13		
N	8	8	8	10	10	12	12	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28	28		
KG	28.78	30.31	31.86	33.41	34.95	36.51	38.05	39.61	41.15	42.69	44.24	45.79	47.35	48.89	50.45	51.99	53.54	55.09	56.64	58.19	59.74	61.28	62.84	64.38	65.94	67.48	69.04		
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1																											
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1																											
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1																											

Stroke	1400	1450	1500	1550	1600	1650	1700	1750	1800	1850	1900	1950	2000	2050				2100			
Limit Stroke (±1)	1410	1460	1510	1560	1610	1660	1710	1760	1810	1860	1910	1960	2010	2060				2110			
L	1810	1860	1910	1960	2010	2060	2110	2160	2210	2260	2310	2360	2410	2460				2510			
A	51	101	31	81	131	61	111	41	91	21	71	121	51	101				31			
M	14	14	15	15	15	16	16	17	17	18	18	18	19	19				20			
N	30	30	32	32	32	34	34	36	36	38	38	38	40	40				42			
KG	70.58	72.12	73.68	75.22	76.78	78.32	79.87	81.42	82.97	84.52	86.07	87.61	89.16	90.71				92.27			
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1												183 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1				167 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1			
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1												367 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1				333 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1			
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1												587 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1				533 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1			

ETH2-14D 1-axis

► Ball Screw Drive

精度
±0.005 mm



Max. stroke 1050mm

Max. Speed 1440mm/s

Motor Output 400W

Ball Screw ø14mm

Linear Guide 15X12.5-2pcs

Ordering Method

ETH2-14D - L6 - 500 - BC - M40B - C3N5L - Refer to the right page. - 0001

Model

Options

Customization Order No.

Stroke

50-1050mm
50 mm Pitch

Sensor location

L Left side
R Right side

Ball Screw Lead

6	6mm
12	12mm
24	24mm

Motor Position

BC	Motor Exposed
BL	Motor Left Side
BR	Motor Right Side
BM	Motor Bottom Side

Motor Brand & Power Output

M	Mitsubishi	10	-	B
P	Panasonic	20	-	
Y	Yaskawa	40	400W	
T	Delta	75	-	

*If No Brake, No Description.

Home Sensor

Out Side	
C	Motor Side
D	Opposite Motor Side
No Sensor	
E	No Sensor


Limit Sensor

Out Side	
3	1 Pc
4	2 Pcs
6	3 Pcs
7	4 Pcs
8	5 Pcs
9	6 Pcs
No Sensor	
5	No Sensor

*When the stroke is 50mm, Home + limit sensors is 2 maximum (only C3/D3/E3/E4/E5 can be selected)

Output type & Cable length

N5	NPN+5M Cable
P2	PNP+2M Cable
P5	PNP+5M Cable
-	NPN+2M Cable




Specification

Performance	Repeatability		mm	±0.005					
	Lead		mm	6		12		24	
	Maximum Rotating speed		rpm	3600	3000	3600	3000	3600	3000
	Maximum linear speed ※1		mm/s	360	300	720	600	1440	1200
	Maximum Payload	Horizontal	kg	110	110	88	88	40	50
		Vertical (No regenerative resistor)	kg	29	33	15	16	9	10
		Vertical (External 200W regenerative resistor)	kg	40	40	26	26	20	20
	Rated Thrust		N	1130		565		283	
	Stroke (increments)		mm	50-1050mm/ (50 increments)					
	Maximum acceleration		G	0.18	0.15	0.37	0.31	0.73	0.61
	Ball screw	Basic dynamic load rating Ca	N	7740		5866		3012	
		Basic static load rating Coa	N	14215		10408		5415	
	Linear Guide	Dynamic horizontal (100km)	N	48193					
		Static Horizontal	N	103488					
	Fixed bearing	Basic dynamic load rating Cr	N	8447					
Static load rating Cor		N	5060						
Parts	AC Servo Motor Output		W	400					
	Ball Screw Ø		mm	C7Ø14					
	High Rigidity Linear Guide		mm	W15XH12.5					
	Coupling		mm	14X10					
	Home Sensor	Outside		T64N(NPN)					


※1 During in a long stroke, it causes ballscrew deflection, the speed must reduce. (Please refer to the linear velocity from the data sheet below the dimension graph.)

Allowable Overhang




(Unit: mm)

Horizontal Installation		A	B	C
Lead 6	60kg	4780	450	130
	70kg	4010	370	107
	110kg	2310	197	57
Lead 12	30kg	3410	860	242
	60kg	1555	376	106
	88kg	961	222	62
Lead 24	20kg	1356	880	218
	40kg	604	387	96
	50kg	454	288	71



(Unit: mm)


Wall Installation		A	B	C
Lead 6	60kg	130	450	4780
	70kg	107	370	4010
	110kg	57	197	2310
Lead 12	30kg	242	860	3410
	60kg	106	376	1555
	88kg	62	222	961
Lead 24	20kg	218	880	1356
	40kg	96	387	604
	50kg	71	288	454



(Unit: mm)

Vertical Installation		A	C
Lead 6	25kg	1229	1229
	30kg	1024	1024
	40kg	768	768
Lead 12	10kg	2439	2439
	15kg	1626	1626
	26kg	938	938
Lead 24	9kg	1485	1485
	10kg	1336	1336
	20kg	668	668

Static Loading Moment



(Unit: N.m)

MY	1149
MP	1149
MR	558

* The data represented by the moment table is the center of gravity of the load. The length of the overhang is allowed in a single direction.

*Operation life is 10,000km when the product is using under the specified conditions.

*Data information is not for ceiling-mount inverse use. Contact us for the details if you want to apply ceiling-mount inverse usage.

*The life and torque are calculated by setting the motor acceleration and deceleration for 0.2 seconds.

Options

P - MM - CMK

Standard PIN hole		
Code	Instructions	Refer to
P	Standard PIN hole	P.677

Selectable Cable Leading Direction		
Code	Instructions	Refer to
MW	Upper side	P.679 ~ P.680
MM	Bottom side	
ML	Left side	
MR	Right side	

Additional keyway for motor drive parts				
Code	Instructions			Refer to
	Keyway Groove	Motor Position	Shipment Type	
CMK	Single (Limited to the motor side)	BC/M	Keyway Coupling	P.681 ~ P.682
		BL/BR/BM	Keyway Belt Pulley	
SKY	Double	BC/M	Keyway Coupling	
		BL/BR/BM	Keyway Belt Pulley	
SKN	Double	BC/M	Without Coupling (Please purchase and install by yourself)	
		BL/BR/BM	Without Belt Pulley (Please purchase and install by yourself)	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-14D 1-axis


► Ball Screw Drive



Download at www.toyorobot.com


BC Motor Exposed (Sensor on the left side)

Unit : mm



BC Motor Exposed (Sensor on the right side)


Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060
L	426	476	526	576	626	676	726	776	826	876	926	976	1026	1076	1126	1176	1226	1276	1326	1376	1426
A	120	50	100	30	80	130	60	110	40	90	20	70	120	50	100	30	80	130	60	110	40
M	2	3	3	4	4	4	5	5	6	6	7	7	7	8	8	9	9	9	10	10	11
N	6	8	8	10	10	10	12	12	14	14	16	16	16	18	18	20	20	20	22	22	24
KG	6.63	7.11	7.59	8.06	8.54	9.01	9.48	9.96	10.44	10.91	11.39	11.86	12.33	12.81	13.29	13.76	14.24	14.71	15.18	15.66	16.14
Linear Speed mm/s	Lead 6																				
	Lead 12																				
	Lead 24																				

Download at www.toyorobot.com**BL Motor Left Side (Sensor on the left side)**

Unit: mm

**BL Motor Left Side (Sensor on the right side)**

Unit: mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060
L	453.5	503.5	553.5	603.5	653.5	703.5	753.5	803.5	853.5	903.5	953.5	1003.5	1053.5	1103.5	1153.5	1203.5	1253.5	1303.5	1353.5	1403.5	1453.5
A	120	50	100	30	80	130	60	110	40	90	20	70	120	50	100	30	80	130	60	110	40
M	2	3	3	4	4	4	5	5	6	6	7	7	8	8	9	9	10	10	10	11	11
N	6	8	8	10	10	10	12	12	14	14	16	16	16	18	18	20	20	20	22	22	24
KG	7.15	7.63	8.1	8.58	9.05	9.53	10	10.48	10.95	11.43	11.9	12.38	12.85	13.33	13.8	14.28	14.75	15.23	15.7	16.18	16.65
Linear Speed mm/s	Lead 6	360					340					300					260				
	Lead 12	720					680					600					520				
	Lead 24	1440					1360					1200					920				

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-14D 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com


BR Motor Right Side (Sensor on the left side)

Unit : mm



BR Motor Right Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060
L	453.5	503.5	553.5	603.5	653.5	703.5	753.5	803.5	853.5	903.5	953.5	1003.5	1053.5	1103.5	1153.5	1203.5	1253.5	1303.5	1353.5	1403.5	1453.5
A	120	50	100	30	80	130	60	110	40	90	20	70	120	50	100	30	80	130	60	110	40
M	2	3	3	4	4	4	5	5	6	6	7	7	8	8	9	9	9	10	10	11	11
N	6	8	8	10	10	10	12	12	14	14	16	16	16	18	18	20	20	20	22	22	24
KG	7.15	7.63	8.1	8.58	9.05	9.53	10	10.48	10.95	11.43	11.9	12.38	12.85	13.33	13.8	14.28	14.75	15.23	15.7	16.18	16.65
Linear Speed mm/s	Lead 6																				
	Lead 12																				
	Lead 24																				

ETH2-17D 1-axis

► Ball Screw Drive

精度
±0.005 mm



Max. stroke 1300mm

Max. Speed 2400mm/s

Motor Output 400W

Ball Screw ø20mm

Linear Guide 15X12.5-2pcs

Ordering Method

ETH2-17D - L5 - 500 - BC - M40B- C3N5L - Refer to the right page. - 0001

Model

Options

Customization Order No.

Stroke

50-1300mm
50 mm Pitch

Sensor location

L Left side
R Right side

Limit Sensor

Out Side	
3	1 Pc
4	2 Pcs
6	3 Pcs
7	4 Pcs
8	5 Pcs
9	6 Pcs
No Sensor	
5	No Sensor

Output type & Cable length

N5	NPN+5M Cable
P2	PNP+2M Cable
P5	PNP+5M Cable
-	NPN+2M Cable

Ball Screw Lead

5	5mm
10	10mm
20	20mm
40	40mm

Motor Position

BC	Motor Exposed
BL	Motor Left Side
BR	Motor Right Side
BM	Motor Bottom Side

Motor Brand & Power Output


M	Mitsubishi	10	-	B
P	Panasonic	20	-	
Y	Yaskawa	40	400W	
T	Delta	75	-	

*If No Brake, No Description.

Home Sensor

Out Side	
C	Motor Side
D	Opposite Motor Side
No Sensor	
E	No Sensor

*When the stroke is 50mm, Home + limit sensors is 2 maximum (only C3/D3/E3/E4/E5 can be selected)




Specification

Performance	Repeatability		mm	±0.005							
	Lead		mm	5		10		20		40	
	Maximum Rotating speed		rpm	3600	3000	3600	3000	3600	3000	3600	3000
	Maximum linear speed ※1		mm/s	300	250	600	500	1200	1000	2400	2000
	Maximum Payload	Horizontal	kg	120	120	110	110	75	85	15	22
		Vertical (No regenerative resistor)	kg	40	50	24	26	10	11	9	10
		Vertical (External 200W regenerative resistor)	kg	50	50	30	30	17	17	15	15
	Rated Thrust		N	1356		678		339		170	
	Stroke (increments)		mm	50-1300mm/(50 increments)							
	Maximum acceleration		G	0.15	0.13	0.31	0.25	0.61	0.51	1.22	1.02
	Ball screw	Basic dynamic load rating Ca	N	17795		10295		5414		6406	
		Basic static load rating Coa	N	45617		22964		10877		15667	
	Linear Guide	Dynamic horizontal (100km)	N	48193							
		Static Horizontal	N	103488							
	Fixed bearing	Basic dynamic load rating Cr	N	9666							
Static load rating Cor		N	6400								
Parts	AC Servo Motor Output		W	400							
	Ball Screw Ø		mm	C7Ø20							
	High Rigidity Linear Guide		mm	W15XH12.5							
	Coupling		mm	14X12							
	Home Sensor	Outside		T64N2(NPN)							


※1 During in a long stroke, it causes ballscrew deflection, the speed must reduce. (Please refer to the linear velocity from the data sheet below the dimension graph.)

Allowable Overhang




(Unit: mm)

Horizontal Installation		A	B	C
Lead 5	70kg	7775	516	141
	90kg	5814	369	101
	120kg	4079	240	66
Lead 10	65kg	2824	484	131
	85kg	2039	336	91
	110kg	1453	227	61
Lead 20	55kg	929	415	105
	75kg	615	266	67
	85kg	512	218	55
Lead 40	10kg	1558	1880	391
	15kg	999	1205	251
	22kg	644	776	161



(Unit: mm)


Wall Installation		A	B	C
Lead 5	70kg	141	516	7775
	90kg	101	369	5814
	120kg	66	240	4079
Lead 10	65kg	131	484	2824
	85kg	91	336	2039
	110kg	61	227	1453
Lead 20	55kg	105	415	929
	75kg	67	266	615
	85kg	55	218	512
Lead 40	10kg	391	1880	1558
	15kg	251	1205	999
	22kg	161	776	644



(Unit: mm)

Vertical Installation		A	C
Lead 5	30kg	1454	1454
	40kg	1090	1090
	50kg	872	872
Lead 10	24kg	1512	1512
	26kg	1396	1396
	30kg	1210	1210
Lead 20	10kg	2347	2347
	11kg	2133	2133
	17kg	1380	1380
Lead 40	9kg	1188	1188
	10kg	1070	1070
	15kg	713	713

Static Loading Moment



(Unit: N.m)

MY	1547
MP	1547
MR	709

* The data represented by the moment table is the center of gravity of the load. The length of the overhang is allowed in a single direction.

* Operation life is 10,000km when the product is using under the specified conditions.

* Data information is not for ceiling-mount inverse use.

Contact us for the details if you want to apply ceiling-mount inverse usage.

* The life and torque are calculated by setting the motor acceleration and deceleration for 0.2 seconds.

Options

P - MM - CMK

Standard PIN hole		
Code	Instructions	Refer to
P	Standard PIN hole	P.677

Selectable Cable Leading Direction		
Code	Instructions	Refer to
MW	Upper side	P.679 ~ P.680
MM	Bottom side	
ML	Left side	
MR	Right side	

Additional keyway for motor drive parts				
Code	Instructions			Refer to
	Keyway Groove	Motor Position	Shipment Type	
CMK	Single (Limited to the motor side)	BC/M	Keyway Coupling	P.681 ~ P.682
		BL/BR/BM	Keyway Belt Pulley	
SKY	Double	BC/M	Keyway Coupling	
		BL/BR/BM	Keyway Belt Pulley	
SKN	Double	BC/M	Without Coupling (Please purchase and install by yourself)	
		BL/BR/BM	Without Belt Pulley (Please purchase and install by yourself)	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-17D 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com •


BC Motor Exposed (Sensor on the left side)

Unit : mm




BC Motor Exposed (Sensor on the right side)

Unit : mm




Stroke		50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300
Limit Stroke (±1)		60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310
L		515	565	615	665	715	765	815	865	915	965	1015	1065	1115	1165	1215	1265	1315	1365	1415	1465	1515	1565	1615	1665	1715	1765
A		89	19	69	119	49	99	29	79	129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	19
M		3	4	4	4	5	5	6	6	6	7	7	8	8	9	9	9	10	10	11	11	11	12	12	13	13	14
N		8	10	10	10	12	12	14	14	14	16	16	18	18	20	20	20	22	22	24	24	24	26	26	28	28	30
KG		9.88	10.46	11.04	11.62	12.2	12.79	13.37	13.95	14.54	15.11	15.7	16.28	16.86	17.45	18.03	18.61	19.19	19.77	20.35	20.94	21.52	22.1	22.68	23.26	23.85	24.43
Linear Speed mm/s	Lead 5	300									275	250	225	200	183	167	150	142	133	117	108	100	92	83	75		
	Lead 10	600									550	500	450	400	367	333	300	283	267	233	217	200	183	167	150		
	Lead 20	1200									1100	1000	900	800	733	667	600	567	533	467	433	400	367	333	300		
	Lead 40	2400									2200	2000	1800	1600	1467	1333	1200	1133	1067	933	867	800	733	667	600		



Download at www.toyorobot.com


BL Motor Left Side (Sensor on the left side)

Unit : mm



BL Motor Left Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310
L	542	592	642	692	742	792	842	892	942	992	1042	1092	1142	1192	1242	1292	1342	1392	1442	1492	1542	1592	1642	1692	1742	1792
A	89	19	69	119	49	99	29	79	129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	19
M	3	4	4	4	5	5	6	6	6	7	7	8	8	9	9	9	10	10	11	11	11	12	12	13	13	14
N	8	10	10	10	12	12	14	14	14	16	16	18	18	20	20	20	22	22	24	24	24	26	26	28	28	30
KG	10.48	11.06	11.65	12.22	12.81	13.39	13.97	14.56	15.14	15.72	16.3	16.88	17.46	18.05	18.63	19.21	19.79	20.37	20.96	21.54	22.12	22.7	23.28	23.87	24.45	25.03
Linear Speed mm/s	Lead 5										275	250	225	200	183	167	150	142	133	117	108	100	92	83	75	
	Lead 10										550	500	450	400	367	333	300	283	267	233	217	200	183	167	150	
	Lead 20										1100	1000	900	800	733	667	600	567	533	467	433	400	367	333	300	
	Lead 40										2200	2000	1800	1600	1467	1333	1200	1133	1067	933	867	800	733	667	600	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-17D 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com •


BR Motor Right Side (Sensor on the left side)

Unit : mm




BR Motor Right Side (Sensor on the right side)

Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310
L	542	592	642	692	742	792	842	892	942	992	1042	1092	1142	1192	1242	1292	1342	1392	1442	1492	1542	1592	1642	1692	1742	1792
A	89	19	69	119	49	99	29	79	129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	19
M	3	4	4	4	5	5	6	6	6	7	7	8	8	9	9	9	10	10	11	11	11	12	12	13	13	14
N	8	10	10	10	12	12	14	14	14	16	16	18	18	20	20	20	22	22	24	24	24	26	26	28	28	30
KG	10.48	11.06	11.65	12.22	12.81	13.39	13.97	14.56	15.14	15.72	16.3	16.88	17.46	18.05	18.63	19.21	19.79	20.37	20.96	21.54	22.12	22.7	23.28	23.87	24.45	25.03
Linear Speed mm/s	Lead 5										275	250	225	200	183	167	150	142	133	117	108	100	92	83	75	
	Lead 10										550	500	450	400	367	333	300	283	267	233	217	200	183	167	150	
	Lead 20										1100	1000	900	800	733	667	600	567	533	467	433	400	367	333	300	
	Lead 40										2200	2000	1800	1600	1467	1333	1200	1133	1067	933	867	800	733	667	600	



Download at www.toyorobot.com


BM Motor Bottom Side (Sensor on the left side)

Unit : mm



BM Motor Bottom Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310
L	555	605	655	705	755	805	855	905	955	1005	1055	1105	1155	1205	1255	1305	1355	1405	1455	1505	1555	1605	1655	1705	1755	1805
A	89	19	69	119	49	99	29	79	129	59	109	39	89	19	69	119	49	99	29	79	129	59	109	39	89	19
M	3	4	4	4	5	5	6	6	6	7	7	8	8	9	9	9	10	10	11	11	11	12	12	13	13	14
N	8	10	10	10	12	12	14	14	14	16	16	18	18	20	20	20	22	22	24	24	24	26	26	28	28	30
KG	10.48	11.06	11.65	12.24	12.81	13.39	13.97	14.56	15.14	15.72	16.3	16.88	17.46	18.05	18.63	19.21	19.79	20.37	20.96	21.54	22.12	22.7	23.28	23.87	24.45	25.03
Linear Speed mm/s	Lead 5										275	250	225	200	183	167	150	142	133	117	108	100	92	83	75	
	Lead 10										550	500	450	400	367	333	300	283	267	233	217	200	183	167	150	
	Lead 20										1100	1000	900	800	733	667	600	567	533	467	433	400	367	333	300	
	Lead 40										2200	2000	1800	1600	1467	1333	1200	1133	1067	933	867	800	733	667	600	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-22D 1-axis

► Ball Screw Drive

精度
±0.005 mm



Max. stroke 1550mm

Max. Speed 1500mm/s

Motor Output 750W

Ball Screw ø25mm

Linear Guide 20X16.3-2pcs

Ordering Method

ETH2-22D - L5 - 500 - BC - M75B- C3N5L - 0001

Model

Options

Customization Order No.

Stroke

50-1550mm
50 mm Pitch

Sensor location

L Left side
R Right side

Limit Sensor

Out Side	
3	1 Pc
4	2 Pcs
6	3 Pcs
7	4 Pcs
8	5 Pcs
9	6 Pcs
No Sensor	
5	No Sensor

Output type & Cable length

N5	NPN+5M Cable
P2	PNP+2M Cable
P5	PNP+5M Cable
-	NPN+2M Cable

Ball Screw Lead

5	5mm
10	10mm
25	25mm

Motor Position

BC	Motor Exposed
BL	Motor Left Side
BR	Motor Right Side
BM	Motor Bottom Side

Motor Brand & Power Output


M	Mitsubishi	10	-	B
P	Panasonic	20	-	
Y	Yaskawa	40	-	
T	Delta	75	750W	

*If No Brake, No Description.

Home Sensor

Out Side	
C	Motor Side
D	Opposite Motor Side
No Sensor	
E	No Sensor

*When the stroke is 50mm, Home + limit sensors is 2 maximum (only C3/D3/E3/E4/E5 can be selected)




Specification

Performance	Repeatability		mm	±0.005					
	Lead		mm	5		10		25	
	Maximum Rotating speed		rpm	3600	3000	3600	3000	3600	3000
	Maximum linear speed ※1		mm/s	300	250	600	500	1500	1250
	Maximum Payload	Horizontal (No regenerative resistor)	kg	150	150	150	150	40	80
		Horizontal (External 200W regenerative resistor)	kg	-	-	-	-	100	105
		Vertical (No regenerative resistor)	kg	55	60	30	33	13	15
		Vertical (External 200W regenerative resistor)	kg	60	65	35	38	18	23
	Rated Thrust		N	2553		1276		511	
	Stroke (increments)		mm	50-1550mm/ (50 increments)					
	Maximum acceleration		G	0.15	0.13	0.31	0.25	0.76	0.64
	Ball screw	Basic dynamic load rating Ca	N	11116		16069		8270	
		Basic static load rating Coa	N	27338		45450		21572	
	Linear Guide	Dynamic horizontal (100km)	N	74176					
		Static Horizontal	N	161040					
Fixed bearing	Basic dynamic load rating Cr	N	22093						
	Static load rating Cor	N	15100						
Parts	AC Servo Motor Output		W	750					
	Ball Screw Ø		mm	C7Ø25					
	High Rigidity Linear Guide		mm	W20XH16.3					
	Coupling		mm	19X17					
	Home Sensor	Outside		T64N2(NPN)					


※1 During in a long stroke, it causes ballscrew deflection, the speed must reduce. (Please refer to the linear velocity from the data sheet below the dimension graph.)

Allowable Overhang




(Unit: mm)

Horizontal Installation	A	B	C
Lead 5	100kg	10507	733
	125kg	8143	549
	150kg	6556	426
Lead 10	100kg	3506	626
	125kg	2674	464
	150kg	2115	355
Lead 25	40kg	1672	1095
	80kg	712	454
	105kg	482	301



(Unit: mm)


Wall Installation	A	B	C
Lead 5	100kg	235	733
	125kg	176	549
	150kg	136	426
Lead 10	100kg	197	626
	125kg	145	464
	150kg	111	355
Lead 25	40kg	301	1095
	80kg	125	454
	105kg	83	301



(Unit: mm)

Vertical Installation	A	C
Lead 5	55kg	1568
	62kg	1391
	65kg	1327
Lead 10	30kg	2381
	33kg	2164
	38kg	1879
Lead 25	13kg	2683
	18kg	1938
	23kg	1516

Static Loading Moment



(Unit: N.m)

MY	3111
MP	3111
MR	1667

* The data represented by the moment table is the center of gravity of the load. The length of the overhang is allowed in a single direction.

* Operation life is 10,000km when the product is using under the specified conditions.

* Data information is not for ceiling-mount inverse use. Contact us for the details if you want to apply ceiling-mount inverse usage.

* The life and torque are calculated by setting the motor acceleration and deceleration for 0.2 seconds.

Options

P - MM - CMK

Standard PIN hole		
Code	Instructions	Refer to
P	Standard PIN hole	P.677

Selectable Cable Leading Direction		
Code	Instructions	Refer to
MW	Upper side	P.679 ~ P.680
MM	Bottom side	
ML	Left side	
MR	Right side	

Additional keyway for motor drive parts				
Code	Instructions			Refer to
	Keyway Groove	Motor Position	Shipment Type	
CMK	Single (Limited to the motor side)	BC/M	Keyway Coupling	P.681 ~ P.682
		BL/BR/BM	Keyway Belt Pulley	
SKY	Double	BC/M	Keyway Coupling	
		BL/BR/BM	Keyway Belt Pulley	
SKN	Double	BC/M	Without Coupling (Please purchase and install by yourself)	
		BL/BR/BM	Without Belt Pulley (Please purchase and install by yourself)	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-22D 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com •


BC Motor Exposed (Sensor on the left side)

Unit : mm



BC Motor Exposed (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560
L	643.5	693.5	743.5	793.5	843.5	893.5	943.5	993.5	1043.5	1093.5	1143.5	1193.5	1243.5	1293.5	1343.5	1393.5	1443.5	1493.5	1543.5	1593.5	1643.5	1693.5	1743.5	1793.5	1843.5	1893.5	1943.5	1993.5	2043.5	2093.5	2143.5
A	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21
M	4	5	5	5	6	6	7	7	7	8	8	9	9	10	10	10	11	11	12	12	12	13	13	14	14	15	15	15	16	16	17
N	10	12	12	12	14	14	16	16	16	18	18	20	20	22	22	22	24	24	26	26	26	28	28	30	30	32	32	32	34	34	36
KG	20.41	21.35	22.28	23.21	24.16	25.1	26.03	26.97	27.9	28.84	29.78	30.72	31.66	32.6	33.53	34.47	35.41	36.35	37.29	38.23	39.16	40.1	41.03	41.97	42.91	43.85	44.78	45.72	46.66	47.6	48.54
Linear Speed mm/s	Lead 5	300									275	250	233	208	192	175	167	150	142	133	125	117	108	100	92	83	75	67			
	Lead 10	600									550	500	467	417	383	350	333	300	283	267	250	233	217	200	183	167	150	133			
	Lead 25	1500									1375	1250	1167	1042	958	875	833	750	708	667	625	583	542	500	458	417	375	333			

ETH2-22D 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com •


BR Motor Right Side (Sensor on the left side)

Unit : mm



BR Motor Right Side (Sensor on the right side)


Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560
L	687.5	737.5	787.5	837.5	887.5	937.5	987.5	1037.5	1087.5	1137.5	1187.5	1237.5	1287.5	1337.5	1387.5	1437.5	1487.5	1537.5	1587.5	1637.5	1687.5	1737.5	1787.5	1837.5	1887.5	1937.5	1987.5	2037.5	2087.5	2137.5	2187.5
A	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21
M	4	5	5	5	6	6	7	7	7	8	8	9	9	10	10	10	11	11	12	12	12	13	13	14	14	15	15	15	16	16	17
N	10	12	12	12	14	14	16	16	16	18	18	20	20	22	22	22	24	24	26	26	26	28	28	30	30	32	32	32	34	34	36
KG	21.49	22.42	23.36	24.29	25.23	26.17	27.11	28.05	28.98	29.92	30.86	31.8	32.74	33.68	34.61	35.55	36.49	37.42	38.36	39.3	40.23	41.17	42.11	43.05	43.99	44.93	45.86	46.8	47.74	48.68	49.62
Linear Speed mm/s	Lead 5	300									275	250	233	208	192	175	167	150	142	133	125	117	108	100	92	83	75	67			
	Lead 10	600									550	500	467	417	383	350	333	300	283	267	250	233	217	200	183	167	150	133			
	Lead 25	1500									1375	1250	1167	1042	958	875	833	750	708	667	625	583	542	500	458	417	375	333			

Download at www.toyorobot.com**BM Motor Bottom Side (Sensor on the left side)**

Unit : mm

**BM Motor Bottom Side (Sensor on the right side)**

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	
L	701.5	751.5	801.5	851.5	901.5	951.5	1001.5	1051.5	1101.5	1151.5	1201.5	1251.5	1301.5	1351.5	1401.5	1451.5	1501.5	1551.5	1601.5	1651.5	1701.5	1751.5	1801.5	1851.5	1901.5	1951.5	2001.5	2051.5	2101.5	2151.5	2201.5	
A	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	
M	4	5	5	5	6	6	7	7	7	8	8	9	9	9	10	10	10	11	11	12	12	12	13	13	14	14	15	15	15	16	16	17
N	10	12	12	12	14	14	16	16	16	18	18	20	20	22	22	22	24	24	26	26	26	28	28	30	30	32	32	32	34	34	36	
KG	21.49	22.42	23.36	24.29	25.23	26.17	27.11	28.05	28.98	29.92	30.86	31.8	32.74	33.68	34.61	35.55	36.49	37.42	38.36	39.3	40.23	41.17	42.11	43.05	43.99	44.93	45.86	46.8	47.74	48.68	49.62	
Linear Speed mm/s	Lead 5	300									275	250	233	208	192	175	167	150	142	133	125	117	108	100	92	83	75	67				
	Lead 10	600									550	500	467	417	383	350	333	300	283	267	250	233	217	200	183	167	150	133				
	Lead 25	1500									1375	1250	1167	1042	958	875	833	750	708	667	625	583	542	500	458	417	375	333				

Features

Standard
Ball Screw Type
ETH2Standard
Belt Type
ETB / MCleanroom
Ball Screw Type
ECH2Cleanroom
Belt Type
ECBMulti Axis Type
XYGT / XTH / XYTB

Reference

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-30D 1-axis

► Ball Screw Drive

精度
±0.005 mm



Max. stroke 1750mm

Max. Speed 1280mm/s

Motor Output 1500W

Ball Screw ø32mm

Linear Guide 23X19.2-2pcs

Ordering Method

ETH2-30D - L10 - 500 - BC - T150B - C3N5L - 0001

Model

Options

Customization Order No.

Stroke

50-1750mm
50 mm Pitch

■ Sensor location

L Left side
R Right side

■ Limit Sensor

Out Side	
3	1 Pc
4	2 Pcs
6	3 Pcs
7	4 Pcs
8	5 Pcs
9	6 Pcs
No Sensor	
5	No Sensor

■ Output type & Cable length

N5	NPN+5M Cable
P2	PNP+2M Cable
P5	PNP+5M Cable
-	NPN+2M Cable

■ Motor Position

BC	Motor Exposed
BL	Motor Left Side
BR	Motor Right Side
BM	Motor Bottom Side

■ Motor Brand & Power Output

M	Mitsubishi	40	-	B
P	Panasonic	75	-	
T	Delta	150	1500W	

*If No Brake, No Description.


■ Home Sensor

Out Side	
C	Motor Side
D	Opposite Motor Side
No Sensor	
E	No Sensor

*When the stroke is 50mm, Home + limit sensors is 2 maximum (only C3/D3/E3/E4/E5 can be selected)

■ Ball Screw Lead

10	10mm
20	20mm
32	32mm




Specification

Performance	Repeatability		mm	±0.005		
	Lead		mm	10	20	32
	Maximum Rotating speed		rpm	2400	2400	2400
	Maximum linear speed ※1		mm/s	400	800	1280
	Maximum Payload	Horizontal (No regenerative resistor)	kg	250	200	20
		Horizontal (External 200W regenerative resistor)	kg	-	-	105
		Vertical (No regenerative resistor)	kg	35	20	10
		Vertical (External 200W regenerative resistor)	kg	48	25	12
	Rated Thrust		N	3824	1912	1195
	Stroke (increments)		mm	50-1750mm/(50 increments)		
	Maximum acceleration		G	0.20	0.41	0.65
	Ball screw	Basic dynamic load rating Ca	N	47137	18708	18031
		Basic static load rating Coa	N	119760	53778	52277
Parts	Linear Guide	Dynamic horizontal (100km)	N	137988		
		Static Horizontal	N	288123		
	Fixed bearing	Basic dynamic load rating Cr	N	25017		
		Static load rating Cor	N	18940		
	AC Servo Motor Output		W	1500		
	Ball Screw Ø		mm	C7Ø32		
	High Rigidity Linear Guide		mm	W23XH19.2		
	Coupling		mm	24X22		
	Home Sensor	Outside		T64N2(NPN)		


※1 During in a long stroke, it causes ballscrew deflection, the speed must reduce. (Please refer to the linear velocity from the data sheet below the dimension graph.)

Allowable Overhang




(Unit : mm)

Horizontal Installation		A	B	C
Lead 10	100kg	19379	1801	726
	200kg	9092	785	316
	250kg	7020	581	234
Lead 20	50kg	13392	3252	1271
	100kg	6409	1510	590
	200kg	2907	640	250
Lead 32	20kg	14030	6485	2376
	50kg	5399	2456	900
	105kg	2382	1048	384



(Unit : mm)


Wall Installation		A	B	C
Lead 10	100kg	726	1801	19379
	200kg	316	785	9092
	250kg	234	581	7020
Lead 20	50kg	1271	3252	13392
	100kg	590	1510	6409
	200kg	250	640	2907
Lead 32	20kg	2376	6485	14030
	50kg	900	2456	5399
	105kg	384	1048	2382



(Unit : mm)

Vertical Installation		A	C
Lead 10	25kg	7680	7680
	35kg	5485	5485
	48kg	4000	4000
Lead 20	20kg	7682	7682
	25kg	6145	6145
	-	-	-
Lead 32	10kg	1063	10635
	12kg	8862	8862
	-	-	-

Static Loading Moment



(Unit : N.m)

MY	6902
MP	6902
MR	4664

* The data represented by the moment table is the center of gravity of the load. The length of the overhang is allowed in a single direction.

* Operation life is 10,000km when the product is using under the specified conditions.

* Data information is not for ceiling-mount inverse use.

Contact us for the details if you want to apply ceiling-mount inverse usage.

* The life and torque are calculated by setting the motor acceleration and deceleration for 0.2 seconds.

Options

P

MM

CMK

Standard PIN hole		
Code	Instructions	Refer to
P	Standard PIN hole	P.677

Selectable Cable Leading Direction		
Code	Instructions	Refer to
MW	Upper side	P.679 ~ P.680
MM	Bottom side	
ML	Left side	
MR	Right side	

Additional keyway for motor drive parts				
Code	Instructions			Refer to
	Keyway Groove	Motor Position	Shipment Type	
CMK	Single (Limited to the motor side)	BC/M	Keyway Coupling	P.681 ~ P.682
		BL/BR/BM	Keyway Belt Pulley	
SKY	Double	BC/M	Keyway Coupling	
		BL/BR/BM	Keyway Belt Pulley	
SKN	Double	BC/M	Without Coupling (Please purchase and install by yourself)	
		BL/BR/BM	Without Belt Pulley (Please purchase and install by yourself)	

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D


ETH2-30D 1-axis



Download at www.toyorobot.com


BC Motor Exposed (Sensor on the left side)

Unit : mm




BC Motor Exposed (Sensor on the right side)

Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960
L	793.5	843.5	893.5	943.5	993.5	1043.5	1093.5	1143.5	1193.5	1243.5	1293.5	1343.5	1393.5	1443.5	1493.5	1543.5	1593.5	1643.5	1693.5
A	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71
M	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13
N	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28
KG	41.08	42.62	44.18	45.73	47.29	48.85	50.41	51.95	53.51	55.06	56.62	58.18	59.73	61.28	62.83	64.39	65.95	67.5	69.06
Linear Speed mm/s	Lead 10																		
	Lead 20																		
	Lead 32																		


Stroke	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750
Limit Stroke (±1)	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760
L	1743.5	1793.5	1843.5	1893.5	1943.5	1993.5	2043.5	2093.5	2143.5	2193.5	2243.5	2293.5	2343.5	2393.5	2443.5	2493.5
A	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31
M	13	14	14	15	15	16	16	17	17	18	18	18	19	19	20	20
N	28	30	30	32	32	34	34	36	36	38	38	38	40	40	42	42
KG	70.6	72.16	73.72	75.28	76.83	78.39	79.93	81.49	83.05	84.6	86.16	87.72	89.26	90.82	92.37	93.93
Linear Speed mm/s	Lead 10															
	Lead 20															
	Lead 32															

Download at www.toyorobot.com**BL Motor Left Side (Sensor on the left side)**

Unit : mm

**BL Motor Left Side (Sensor on the right side)**

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950
Limit Stroke (± 1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960
L	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710
A	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71
M	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13
N	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28
KG	43.4	44.95	46.5	48.06	49.62	51.18	52.73	54.28	55.83	57.39	58.95	60.5	62.06	63.6	65.16	66.72	68.27	69.83	71.39
Linear Speed mm/s	400																		
	800																		
	1280																		

Stroke	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750
Limit Stroke (± 1)	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760
L	1760	1810	1860	1910	1960	2010	2060	2110	2160	2210	2260	2310	2360	2410	2460	2510
A	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31
M	13	14	14	15	15	16	16	17	17	18	18	18	18	19	19	20
N	28	30	30	32	32	34	34	36	36	38	38	38	38	40	40	42
KG	72.93	74.49	76.05	77.6	79.16	80.72	82.26	83.82	85.37	86.93	88.49	90.04	91.59	93.14	94.7	96.26
Linear Speed mm/s	383															
	367															
	333															
Lead 20	317															
	300															
	283															
Lead 32	267															
	533															
	500															
Lead 32	467															
	433															
	400															
Lead 32	367															
	333															
	300															
Lead 32	267															
	233															
	200															
Lead 32	183															
	167															
	150															
Lead 32	133															
	117															
	100															
Lead 32	83															
	67															
	50															
Lead 32	33															
	17															
	0															

ETH2-30D 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com •


BR Motor Right Side (Sensor on the left side)

Unit : mm




BR Motor Right Side (Sensor on the right side)

Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960
L	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710
A	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71
M	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13
N	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28
KG	43.4	44.95	46.5	48.06	49.62	51.18	52.73	54.28	55.83	57.39	58.95	60.5	62.06	63.6	65.16	66.72	68.27	69.83	71.39
Linear Speed mm/s	Lead 10	400																	
	Lead 20	800																	
	Lead 32	1280																	
Stroke	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750			
Limit Stroke (±1)	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760			
L	1760	1810	1860	1910	1960	2010	2060	2110	2160	2210	2260	2310	2360	2410	2460	2510			
A	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31			
M	13	14	14	15	15	16	16	17	17	18	18	18	19	19	20	20			
N	28	30	30	32	32	34	34	36	36	38	38	38	40	40	42	42			
KG	72.93	74.49	76.05	77.6	79.16	80.72	82.26	83.82	85.37	86.93	88.49	90.04	91.59	93.14	94.7	96.26			
Linear Speed mm/s	Lead 10	383	367	333	317	300	283	267	250	233	217	200	183	167	150	133			
	Lead 20	767	733	667	633	600	567	533	500	467	433	400	367	333	300	267			
	Lead 32	1227	1173	1067	1013	960	907	853	800	747	693	640	587	533	480	427			



Download at www.toyorobot.com


BM Motor Bottom Side (Sensor on the left side)

Unit : mm



BM Motor Bottom Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960
L	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710
A	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71
M	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13
N	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28
KG	42.32	43.86	45.42	46.97	48.53	50.09	51.64	53.19	54.74	56.3	57.86	59.41	60.97	62.51	64.07	65.63	67.19	68.74	70.3
Linear Speed mm/s	400																		
	800																		
	1280																		

Stroke	1000	1050	1100	1150	1200	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750
Limit Stroke (±1)	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760
L	1760	1810	1860	1910	1960	2010	2060	2110	2160	2210	2260	2310	2360	2410	2460	2510
A	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31
M	13	14	14	15	15	15	16	16	17	17	18	18	18	19	19	20
N	28	30	30	32	32	32	34	34	36	36	38	38	38	40	40	42
KG	71.84	73.4	74.96	76.51	78.07	79.63	81.17	82.73	84.28	85.84	87.4	88.96	90.5	92.06	93.61	95.17
Linear Speed mm/s	383															
	367															
	333															
Lead 20	317															
	300															
	283															
Lead 32	267															
	533															
	500															
Lead 32	747															
	693															
	640															

ETH2-30D 1-axis

► Ball Screw Drive^e

精度
±0.005
mm



Max. stroke 1750mm

Max. Speed 640mm/s

Motor Output 750W

Ball Screw ø32mm

Linear Guide 23X19.2-2pcs


Ordering Method

ETH2-30D-L10-500-BC-M75B-C3N5L-03-0001

Model				Options		Customization Order No.
				Sensor location		Slide
				L Left side		3 3:1
				R Right side		5 5:1
				Limit Sensor		Output type & Cable length
				Out Side		N5 NPN+5M Cable
				3 1 Pc		P2 PNP+2M Cable
				4 2 Pcs		P5 PNP+5M Cable
				6 3 Pcs		- NPN+2M Cable
				7 4 Pcs		
				8 5 Pcs		
				9 6 Pcs		
				No Sensor		
				5 No Sensor		
				Home Sensor		
				Out Side		
				C Motor Side		
				D Opposite Motor Side		
				No Sensor		
				E No Sensor		
				Motor Position		
				BC Motor Exposed		
				BL Motor Left Side		
				BR Motor Right Side		
				BM Motor Bottom Side		
				Motor Brand & Power Output		
				M Mitsubishi 10 - B		
				P Panasonic 20 -		
				Y Yaskawa 40 -		
				T Delta 75 750W		
				Ball Screw Lead		
				10 10mm		
				20 20mm		
				32 32mm		
				Stroke		
				50-1750mm		
				50 mm Pitch		

*If No Brake, No Description.

*When the stroke is 50mm, Home + limit sensors is 2 maximum (only C3/D3/E3/E4/E5 can be selected)




Specification

Performance	Repeatability		mm	±0.005					
	Lead		mm	10		20		32	
	Reduce Ratio			3:1	5:1	3:1	5:1	3:1	5:1
	Maximum Rotating speed		rpm	3600		3600		3600	
	Maximum linear speed ※1		mm/s	200	120	400	240	640	384
	Maximum Payload	Horizontal	kg	400	400	300	300	180	180
		Vertical (No regenerative resistor)	kg	110	155	55	75	20	38
		Vertical (External 200W regenerative resistor)	kg	130	200	65	110	38	60
	Rated Thrust		N	3829	6382	1915	3191	1197	1994
	Stroke (increments)		mm	50-1750mm/(50 increments)					
	Maximum acceleration		G	0.10	0.06	0.20	0.12	0.33	0.20
	Ball screw	Basic dynamic load rating Ca	N	47137		18708		18031	
		Basic static load rating Coa	N	119760		53778		52277	
	Linear Guide	Dynamic horizontal (100km)	N	137988					
		Static Horizontal	N	288123					
Fixed bearing	Basic dynamic load rating Cr	N	25017						
	Static load rating Cor	N	18940						
Parts	AC Servo Motor Output		W	750					
	Ball Screw Ø		mm	C7Ø32					
	High Rigidity Linear Guide		mm	W23XH19.2					
	Coupling		mm	22X22					
	Home Sensor	Outside		T64N2(NPN)					


※1 During in a long stroke, it causes ballscrew deflection, the speed must reduce. (Please refer to the linear velocity from the data sheet below the dimension graph.)

Allowable Overhang




(Unit: mm)

Horizontal Installation		A	B	C
Lead 10	200kg	33490	930	378
	300kg	21427	543	220
	400kg	15288	349	142
Lead 20	100kg	23750	1801	729
	200kg	11269	785	318
	300kg	7062	446	180
Lead 32	80kg	14405	2078	834
	130kg	8583	1190	477
	180kg	5988	795	319



(Unit: mm)


Wall Installation		A	B	C
Lead 10	200kg	378	930	33490
	300kg	220	543	21427
	400kg	142	349	15288
Lead 20	100kg	729	1801	23750
	200kg	318	785	11269
	300kg	180	446	7062
Lead 32	80kg	834	2078	14405
	130kg	477	1190	8583
	180kg	319	795	5988



(Unit: mm)

Vertical Installation		A	C
Lead 10	110kg	2077	2077
	155kg	1474	1474
	200kg	1142	1142
Lead 20	55kg	3575	3575
	75kg	2621	2621
	110kg	1787	1787
Lead 32	20kg	8725	8725
	38kg	4592	4592
	60kg	2908	2908

Static Loading Moment



(Unit: N.m)

MY	6902
MP	6902
MR	4664

* The data represented by the moment table is the center of gravity of the load. The length of the overhang is allowed in a single direction.

* Operation life is 10,000km when the product is using under the specified conditions.

* Data information is not for ceiling-mount inverse use.

Contact us for the details if you want to apply ceiling-mount inverse usage.

* The life and torque are calculated by setting the motor acceleration and deceleration for 0.2 seconds.

Options

P - **MM** - **CMK**

Standard PIN hole		
Code	Instructions	Refer to
P	Standard PIN hole	P.677

Selectable Cable Leading Direction		
Code	Instructions	Refer to
MW	Upper side	P.679 ~ P.680
MM	Bottom side	
ML	Left side	
MR	Right side	

Additional keyway for motor drive parts			
Code	Instructions		
	Keyway Groove	Motor Position	Shipment Type
CMK	Single (Limited to the motor side)	BC/M	Keyway Coupling
		BL/BR/BM	Keyway Belt Pulley
SKY	Double	BC/M	Keyway Coupling
		BL/BR/BM	Keyway Belt Pulley
SKN	Double	BC/M	Without Coupling (Please purchase and install by yourself)
		BL/BR/BM	Without Belt Pulley (Please purchase and install by yourself)

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D

ETH2-22D

ETH2-30D

ETH2-30D 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com •


BC Motor Exposed (Sensor on the left side)

Unit : mm




BC Motor Exposed (Sensor on the right side)

Unit : mm




Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210
L	786.5	836.5	886.5	936.5	986.5	1036.5	1086.5	1136.5	1186.5	1236.5	1286.5	1336.5	1386.5	1436.5	1486.5	1536.5	1586.5	1636.5	1686.5	1736.5	1786.5	1836.5	1886.5	1936.5
A	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81
M	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13	13	14	14	15	15
N	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28	28	30	30	32	32
KG	44.18	45.73	47.28	48.84	50.4	51.95	53.5	55.05	56.61	58.17	59.73	61.28	62.84	64.38	65.94	67.5	69.05	70.61	72.17	73.71	75.27	76.82	78.38	79.94
Linear Speed mm/s	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1																							
	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1																							
	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1																							


Stroke		1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750		
Limit Stroke (±1)		1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760		
L		1986.5	2036.5	2086.5	2136.5	2186.5	2236.5	2286.5	2336.5	2386.5	2436.5	2486.5		
A		131	61	111	41	91	21	71	121	51	101	31		
M		15	16	16	17	17	18	18	18	19	19	20		
N		32	34	34	36	36	38	38	38	40	40	42		
KG		81.5	83.04	84.6	86.15	87.71	89.27	90.82	92.37	93.92	95.48	97.04		
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1								183 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1			167 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1	
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1								367 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1			333 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1	
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1								587 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1			533 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1	

Download at www.toyorobot.com**BL Motor Left Side (Sensor on the left side)**

Unit : mm

**BL Motor Left Side (Sensor on the right side)**

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200	
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210	
L	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760	1810	1860	1910	1960	
A	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81	
M	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13	13	14	14	15	15	
N	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28	28	30	30	32	32	
KG	46.62	48.16	49.72	51.28	52.83	54.39	55.95	57.49	59.05	60.61	62.16	63.72	65.28	66.82	68.38	69.93	71.49	73.05	74.6	76.15	77.7	79.26	80.82	82.38	
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1																							
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1																							
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1																							

Stroke	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750	
Limit Stroke (±1)	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760	
L	2010	2060	2110	2160	2210	2260	2310	2360	2410	2460	2510	
A	131	61	111	41	91	21	71	121	51	101	31	
M	15	16	16	17	17	18	18	18	19	19	20	
N	32	34	34	36	36	38	38	38	40	40	42	
KG	83.93	85.48	87.03	88.59	90.15	91.7	93.26	94.8	96.36	97.92	99.47	
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1							183 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1		167 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1	
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1							367 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1		333 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1	
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1							587 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1		533 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1	

ETH2-30D 1-axis


► Ball Screw Drive



• Download at www.toyorobot.com •


BR Motor Right Side (Sensor on the left side)

Unit : mm




BR Motor Right Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210
L	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760	1810	1860	1910	1960
A	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81
M	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13	13	14	14	15	15
N	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28	28	30	30	32	32
KG	46.62	48.16	49.72	51.28	52.83	54.39	55.95	57.49	59.05	60.61	62.16	63.72	65.28	66.82	68.38	69.93	71.49	73.05	74.6	76.15	77.7	79.26	80.82	82.38
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1																						
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1																						
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1																						


Stroke	1250	1300	1350	1400	1450	1500	1550	1600	1650				1700				1750								
Limit Stroke (±1)	1260	1310	1360	1410	1460	1510	1560	1610	1660				1710				1760								
L	2010	2060	2110	2160	2210	2260	2310	2360	2410				2460				2510								
A	131	61	111	41	91	21	71	121	51				101				31								
M	15	16	16	17	17	18	18	18	19				19				20								
N	32	34	34	36	36	38	38	38	40				40				42								
KG	83.93	85.48	87.03	88.59	90.15	91.7	93.26	94.8	96.36				97.92				99.47								
Linear Speed mm/s	Lead 10	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1								183 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1								167 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1							
	Lead 20	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1								367 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1								333 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1							
	Lead 32	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1								587 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1								533 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1							



Download at www.toyorobot.com


BM Motor Bottom Side (Sensor on the left side)

Unit : mm



BM Motor Bottom Side (Sensor on the right side)

Unit : mm



Stroke	50	100	150	200	250	300	350	400	450	500	550	600	650	700	750	800	850	900	950	1000	1050	1100	1150	1200
Limit Stroke (±1)	60	110	160	210	260	310	360	410	460	510	560	610	660	710	760	810	860	910	960	1010	1060	1110	1160	1210
L	810	860	910	960	1010	1060	1110	1160	1210	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760	1810	1860	1910	1960
A	131	61	111	41	91	21	71	121	51	101	31	81	131	61	111	41	91	21	71	121	51	101	31	81
M	5	6	6	7	7	8	8	8	9	9	10	10	10	11	11	12	12	13	13	13	14	14	15	15
N	12	14	14	16	16	18	18	18	20	20	22	22	22	24	24	26	26	28	28	30	30	32	32	32
KG	45.55	47.09	48.65	50.21	51.76	53.32	54.88	56.42	57.98	59.53	61.09	62.65	64.2	65.75	67.3	68.86	70.42	71.98	73.53	75.08	76.63	78.19	79.75	81.3
Linear Speed mm/s	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1																							
	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1																							
	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1																							

Stroke	1250	1300	1350	1400	1450	1500	1550	1600	1650	1700	1750
Limit Stroke (±1)	1260	1310	1360	1410	1460	1510	1560	1610	1660	1710	1760
L	2010	2060	2110	2160	2210	2260	2310	2360	2410	2460	2510
A	131	61	111	41	91	21	71	121	51	101	31
M	15	16	16	17	17	18	18	18	19	19	20
N	32	34	34	36	36	38	38	38	40	40	42
KG	82.86	84.4	85.96	87.52	89.07	90.63	92.19	93.73	95.29	96.85	98.4
Linear Speed mm/s	200 Reduce Ratio 3:1 / 120 Reduce Ratio 5:1										
	400 Reduce Ratio 3:1 / 240 Reduce Ratio 5:1										
	640 Reduce Ratio 3:1 / 384 Reduce Ratio 5:1										

ETH2 Series

ETH2-14

ETH2-17

ETH2-22

ETH2-30

ETH2-14D

ETH2-17D


ETH2-22D

ETH2-30D

Mitsubishi Servo Motor Information

Servo Motor		No Brake	HG-AK0336	HG-KR053	HG-KR13	HG-KR23	HG-KR43	HG-KR73	HG-SR102	HG-SR152
		With Brake	HG-AK0336B	HG-KR053B	HG-KR13B	HG-KR23B	HG-KR43B	HG-KR73B	HG-SR102B	HG-SR152B
Motor Drives			MR-J3W-0303BN6	MR-J4-10A	MR-J4-10A	MR-J4-20A	MR-J4-40A	MR-J4-70A	MR-J4-100A	MR-J4-200A
Power Supply Capacity			480(W)	0.3	0.3	0.5	0.9	1.3	1.7	2.5
Power Consumption			30	50	100	200	400	750	1000	1500
Rated Torque			0.095	0.16	0.32	0.64	1.3	2.4	4.8	7.2
Instantaneous Maximum Torque			0.286	0.56	1.1	2.2	4.5	8.4	14.3	21.5
Rated Current			2.2	0.9	0.8	1.3	2.6	4.8	5.6	9.4
Maximum Current			6.6	3.2	2.5	4.6	9.1	17	17	29
Rated Speed			3000						2000	
Maximum Speed			6000						3000	
load Inertia (X10 ⁻⁴ kg.m ²)	No Brake		0.0061	0.045	0.0777	0.221	0.371	1.26	11.6	16
	With Brake		0.0074	0.0472	0.0837	0.243	0.393	1.37	13.8	18.2
Load Inertia Moment Ratio			Under 30 Multiple	Under 17 Multiple		Under 26 Multiple	Under 25 Multiple	Under 17 Multiple		
Controller	Type		Incremental, Share With Controller							
		18bit	22bit							
	Encoder Resolutiess Of Servo Motor		262144 p/rev	4194304 p/rev						
Structure (Natural-cooling,Open)			IP Rating:IP55	IP Rating:IP66					IP Rating:IP67	
Environmental Conditions	Ambient Temperature		0°C ~40°C Non-freezing, -15°C ~70°C Non-freezing							
	Ambient Humidity		10%RH~80%RH Non-freezing , 10%RH~90%RH Non-condensing							
	Ambience		Indoors(no direct sunlight), Free From Corrosive Gas, Flammable Gas, Oil Mist, Dust, And Dirt.							
	Altitude		Max. 1000 m Above Sea Level	Max. 2000 m Above Sea Level						
	Vibration		X:49m/s2 Y:49m/s2						X:24.5m/s2 Y:24.5m/s2	
Weight(kg)	No Brake		0.16	0.34	0.54	0.91	1.4	2.8	6.2	7.3
	With Brake		0.26	0.54	0.74	1.3	1.8	3.8	8.2	9.3


Model	30W	L
HG-AK0336	No Brake	68
HG-AK0336B	With Brake	100



30W


Model	50W	L
HG-KR053	No Brake	66.4
HG-KR053B	With Brake	107

Model	100W	L
HG-KR13	No Brake	82.4
HG-KR13B	With Brake	123




50/100W


Model	200W	L
HG-KR23	No Brake	76.6
HG-KR23B	With Brake	113.4

**200W**


Model	400W	L
HG-KR43	No Brake	98.3
HG-KR43B	With Brake	135.1

**400W**


Model	750W	L
HG-KR73	No Brake	112
HG-KR73B	With Brake	152.3

**750W**

Model	1000W	L
HG-SR102	No Brake	132.5
HG-SR102B	With Brake	167

**1000W**

Model	1500W	L
HG-SR152	No Brake	146.5
HG-SR152B	With Brake	181

**1500W**


Panasonic Servo Motor Information

Servo Motor	No Brake	MSMF5AZL1U	MSMF012L1U	MHMF022L1U	MHMF042L1U	MHMF082L1U	MDMF102L1G	MDMF152L1G	
	With Brake	MSMF5AZL1V	MSMF012L1V	MHMF022L1V	MHMF042L1V	MHMF082L1V	MDMF102L1H	MDMF152L1H	
Motor Drives		MADLT05SF	MADLT05SF	MADLT15SF	MBDLT25SF	MCDLT35SF	MDDLT45SF	MDDLT55SF	
Power Supply Capacity		0.5	0.5	0.5	0.9	1.8	2.4	2.9	
Power Consumption		50	100	200	400	750	1000	1500	
Rated Torque		0.16	0.32	0.64	1.27	2.39	4.77	7.16	
Instantaneous Maximum Torque		0.48	0.95	2.23	4.46	8.36	14.3	21.5	
Rated Current		1.1	1.1	1.4	2.1	3.8	5.2	8	
Maximum Current		4.7	4.7	6.9	10.4	18.8	22	34	
Rated Speed		3000					2000		
Maximum Speed		6000					3000		
load Inertia (X10 ⁻⁴ kg.m ²)	No Brake	0.026	0.048	0.29	0.56	1.56	6.18	9.16	
	With Brake	0.029	0.051	0.31	0.58	1.66	7.4	10.4	
Load Inertia Moment Ratio		Under 30 Multiple					Under 20 Multiple	Under 10 Multiple	
Controller	Pulse	Absolute / Incremental 23-bit Encoder							
	Resolution	8388608 p/rev							
Structure		Natural-cooling,Open (IP Rating:IP65)							
Environmental Conditions	Ambient Temperature	0℃ ~40℃ Non-freezing, Storage: -20℃ to 65℃ (Maximum Temperature Tolerance: 80℃ for up to 72 hours,							
	Ambient Humidity	20%RH~85%RH No Condensation							
	Ambience	Indoors(no direct sunlight), Free From Corrosive Gas, Flammable Gas, Oil Mist, Dust, And Dirt.							
	Altitude	Max. 1000 m Above Sea Level							
	Vibration	During Operation: ≤ 49 m/s² (5G); When Stopped: ≤ 24.5 m/s² (2.5G)							
Weight(kg)	No Brake	0.32	0.47	0.81	1.2	2.4	4.6	5.7	
	With Brake	0.53	0.68	1.2	1.6	3.1	6.1	7.2	

Model	50W	L
MSMF5AZL1U	No Brake	72
MSMF5AZL1V	With Brake	102


Model	100W	L
MSMF012L1U	No Brake	92
MSMF012L1V	With Brake	122

50/100W



Model	200W	L
MHMF022L1U	No Brake	71
MHMF022L1V	With Brake	100.3

200W




免費服務專線：台灣 0800-800-893
Toll-free Number Taiwan

Features	Standard Ball Screw Type ETH2	Standard Belt Type ETB / M	Cleanroom Ball Screw Type ECH2	Cleanroom Belt Type ECB	Multi Axis Type XYGT / XTH / XYTB	Reference
----------	-------------------------------	----------------------------	--------------------------------	-------------------------	-----------------------------------	-----------


Model	400W	L
MHMF042L1U	No Brake	88
MHMF042L1V	With Brake	117.3

400W




Model	750W	L
MHMF082L1U	No Brake	95.4
MHMF082L1V	With Brake	129

750W




Model	1000W	L
MDMF102L1G	No Brake	122
MDMF102L1H	With Brake	150

1000W




Model	1500W	L	J
MDMF152L1G	No Brake	136	(105)
MDMF152L1H	With Brake	164	(116)

1500W




400W

Model	400W	L
ECMA-C20604ES	No Brake	130.7
ECMA-C20604FS	With Brake	166.8




750W

Model	750W	L
ECMA-C20807ES	No Brake	138.3
ECMA-C20807FS	With Brake	178




1000W

Model	1000W	L
ECMA-E11310ES	No Brake	147.5
ECMA-E11310FS	With Brake	183.5



1500W

Model	1500W	L
ECMA-E11315ES	No Brake	167.5
ECMA-E11315FS	With Brake	202




Yaskawa Servo Motor Information

Servo Motor	No Brake	SGMMV-A3A2A21	SGMJV-A5AAA21	SGMJV-01AAA21	SGMJV-02AAA21	SGMJV-04AAA21	SGMJV-08AAA21	SGMSV-10ADA21
	With Brake	SGMMV-A3A2A2C	SGMJV-A5A3A2C	SGMJV-01AAA2C	SGMJV-02AAA2C	SGMJV-04AAA2C	SGMJV-08AAA2C	SGMSV-10ADA2C
Motor Drives	single phase220V	SGDV-2R1F	SGDV-R70F	SGDV-R90F	SGDV-2R1F	SGDV-2R8F	—	—
	Three Phase220V	SGDV-1R6A	SGDV-R70A	SGDV-R90A	SGDV-1R6A	SGDV-2R8A	SGDV-5R5A	SGDV-7R6A
Power Consumption		30	50	100	200	400	750	1000
Rated Torque		0.0955	0.159	0.318	0.637	1.27	2.39	3.18
Instantaneous Maximum Torque		0.286	0.557	1.11	2.23	4.46	8.36	9.54
Rated Current		0.98	0.61	0.84	1.6	2.7	4.7	5.7
Maximum Current		2.9	2.1	2.9	5.8	9.3	16.9	17
Rated Speed		3000						
Maximum Speed		6000						
load Inertia (X10-4 kg.m2)	No Brake	0.00668	0.0414	0.0665	0.259	0.442	1.57	1.74
	With Brake	0.00804	0.0561	0.0812	0.323	0.744	1.74	1.99
Load Inertia Moment Ratio		Under 30 Multiple	Under 20 Multiple		Under 15 Multiple	Under 10 Multiple		Under 5 Multiple
Controller	Type	絕對值 17bit 之編碼器	No Brake	增量型 13bit 之編碼器				增量型 20 bit
			增量型 13bit 之編碼器					
			With Brake					
			絕對值 20bit 之編碼器					
Structure		Natural-cooling,Open (IP Rating:IP55)	Natural-cooling,Open (IP Rating:IP65)					IP67
Environmental Conditions	Ambient Temperature	0°C ~40°C , -10°C ~80°C Non-freezing						
	Ambient Humidity	20%~80%RH Non-condensing						
	Ambience	V15						
	Altitude	B						F
	Vibration	AC1500V 1min						
Weight(kg)	No Brake	0.21	0.3	0.4	0.9	1.3	2.7	4.1
	With Brake	0.31	0.6	0.7	1.5	1.9	3.6	5.5


Model	30W	L
SGMMV-A3A2A21	No Brake	74
SGMMV-A3A2A2C	With Brake	102.5

30W




Model	50W	L
SGMJV-A5AAA21	No Brake	69
SGMJV-A5A3A2C	With Brake	114
Model	100W	L
SGMJV-01AAA21	No Brake	82.5
SGMJV-01AAA2C	With Brake	127.5

50/100W




Model	200W	L
SGMJV-02AAA21	No Brake	80
SGMJV-02AAA2C	With Brake	120

200W




Model	400W	L
SGMJV-04AAA21	No Brake	98.5
SGMJV-04AAA2C	With Brake	138.5

400W






Model	750W	L
SGMJV-08AAA21	No Brake	115
SGMJV-08AAA2C	With Brake	160

750W



Options

Additional standard PIN hole

Code		Instructions
P		Additional standard PIN hole
Applicable	Motor direction	
ETH2-14 ETH2-17 ECH2-14 ECH2-17	BC BM BL BR	 ※ Using ETH2-14 as an example
ETH2-22 ECH2-22	BC BM BL BR	 ※ Using ETH2-22 as an example
ETH2-30	BC BM BL BR	 ※ Using ETH2-30 as an example

PIN hole size table

Model	Aperture ØH (mm)	Depth D (mm)	Oval hole center distance W (mm)
ETH2-14/ECH2-14	6	6	2
ETH2-17/ECH2-17	6	6	2
ETH2-22/ECH2-22	6	6	2
ETH2-30	8	8	2

免費服務專線：台灣 0800-800-893
Toll-Free Number Taiwan

Selectable Motor Cable Leading Direction

Code	Instructions	Diagram
MW	Motor cable leading direction upper side	
MR	Motor cable leading direction Right side	
MM	Motor cable leading direction Bottom side	
ML	Motor cable leading direction Left side	



※Definition method of the outlet direction 1. The slide table is placed horizontally 2. Face the motor output shaft, judge up, down, left and right

Ball Screw type	Motor position corresponds to power cable direction															
	BC				BL				BR				BM			
Applicable specs	MW	MR	MM	ML	MW	MR	MM	ML	MW	MR	MM	ML	MW	MR	MM	ML
ETH2 series ECH2 series	○	○	○	○	○	○	○	×	○	×	○	○	×	○	○	○



Features	Standard Ball Screw Type ETH2
	Standard Belt Type ETB / M
	Cleanroom Ball Screw Type ECH2
	Cleanroom Belt Type ECB
	Multi Axis Type XYGT / XTH / XYTB
Reference	

Options

Selectable Motor Cable Leading Direction

Applicable specs	Provide motor cable leading direction example according to different specifications
ETH2 series ECH2 series	 ※ Using ETH as an example
	 ※ Using ETH as an example ※ This example cannot be used with ML, it will interfere with the slider

Additional Keyway for Motor Transmission Accessories

Code		Instructions
CMK		Additional keyway for motor transmission accessories (only one side - limited to the motor side)
Applicable specs	Motor position	Schematic diagram of additional keyway on one side
ETH2 series ECH2 series	BC M	Additional keyway at the motor end  Dimensions of keyway coupling Motor end (keyway type) Screw end (clamp type) ※ Using GTH as an example
	BL BR BM	 Screw end (clamp type) Motor end (keyway type) Dimensions of keyway pulley Additional keyway at the motor end ※ Using GTH as an example

Features

Standard
Ball Screw Type
ETH2

Standard
Belt Type
ETB / M

Cleanroom
Ball Screw Type
ECH2



Cleanroom
Belt Type
ECB

Multi Axis Type
XYGT / XTH / XYTB

Reference

Options

Additional Keyway for Motor Transmission Accessories

Code		Instructions
SKY		Additional keyway at motor end & screw end Shipment with keyway parts
SKN		Additional keyway at the motor end & screw end Shipment without keyway parts (purchased and installed by the customer)
Applicable	Motor position	Schematic diagram of additional keyway on both sides
ETH2 series ECH2 series	BC M	 Additional keyway at the motor end Additional keyway at screw end Dimensions of keyway coupling → Motor end (keyway type) Screw end (Keyway type) ※ Using GTH as an example
	BL BR BM	 Additional keyway at screw end Additional keyway at the motor end Dimensions of keyway pulley ← Screw end (Keyway type) Motor end (keyway type) ※ Using GTH as an example

免費服務專線：台灣 0800-800-893
Toll-Free Number Taiwan

Dimensions corresponding to the keyway of each specification								
Bulit-in linear Guide ball screw actuator/electric cylinder		Ball Screw actuator / servo electric cylinder		Motor wattage	Motor ShaftØ (mm)(d1)	Keyway Width (mm)(W1)	Ball screw processing end (mm)(d2)	Keyway size (mm) (W2)
General environment	Clean room environment	General environment	Clean room environment					
—	—	ETH2-14	ECH2-14	400W	14	5	10	3
—	—	ETH2-17	ECH2-17	400W			12	4
—	—	ETH2-22	ECH2-22	750W	19	6	17	5
—	—	ETH2-30	—	750W+ Gearbox	22	6	22	6
—	—			T1500W P1500W				
—	—			M1500W	24	8		

*If it does not meet the above definition, a corresponding special order is required.
*This code is not applicable when the motor shaft is flat (non-keyway), such as Mitsubishi 100W.

Features
Standard Ball Screw Type ETH2
Standard Belt Type ETB / M
Cleanroom Ball Screw Type ECH2
Cleanroom Belt Type ECB
Multi Axis Type XYGT / XTH / XYTB
Reference